

A. Introduction

1. **Title:** **Reliability Coordination — Current Day Operations**
2. **Number:** IRO-005-3
3. **Purpose:** The Reliability Coordinator must be continuously aware of conditions within its Reliability Coordinator Area and include this information in its reliability assessments. The Reliability Coordinator must monitor Bulk Electric System parameters that may have significant impacts upon the Reliability Coordinator Area and neighboring Reliability Coordinator Areas.
4. **Applicability**
 - 4.1. Reliability Coordinators.
 - 4.2. Balancing Authorities.
 - 4.3. Transmission Operators.
 - 4.4. Transmission Service Providers.
 - 4.5. Generator Operators.
 - 4.6. Load-Serving Entities.
 - 4.7. Purchasing-Selling Entities.
5. **Effective Date:**

In those jurisdictions where no regulatory approval is required, the standard shall become effective on the latter of either April 1, 2009 or the first day of the first calendar quarter, three months after BOT adoption.

In those jurisdictions where regulatory approval is required, the standard shall become effective on the latter of either April 1, 2009 or the first day of the first calendar quarter, three months after applicable regulatory approval.

B. Requirements

- R1. Each Reliability Coordinator shall monitor its Reliability Coordinator Area parameters, including but not limited to the following:
 - R1.1. Current status of Bulk Electric System elements (transmission or generation including critical auxiliaries such as Automatic Voltage Regulators and Special Protection Systems) and system loading.
 - R1.2. Current pre-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan's viability and scope.
 - R1.3. Current post-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan's viability and scope.
 - R1.4. System real and reactive reserves (actual versus required).
 - R1.5. Capacity and energy adequacy conditions.
 - R1.6. Current ACE for all its Balancing Authorities.

- R1.7.** Current local or Transmission Loading Relief procedures in effect.
- R1.8.** Planned generation dispatches.
- R1.9.** Planned transmission or generation outages.
- R1.10.** Contingency events.
- R2.** Each Reliability Coordinator shall monitor its Balancing Authorities' parameters to ensure that the required amount of operating reserves is provided and available as required to meet the Control Performance Standard and Disturbance Control Standard requirements. If necessary, the Reliability Coordinator shall direct the Balancing Authorities in the Reliability Coordinator Area to arrange for assistance from neighboring Balancing Authorities. The Reliability Coordinator shall issue Energy Emergency Alerts as needed and at the request of its Balancing Authorities and Load-Serving Entities.
- R3.** Each Reliability Coordinator shall ensure its Transmission Operators and Balancing Authorities are aware of Geo-Magnetic Disturbance (GMD) forecast information and assist as needed in the development of any required response plans.
- R4.** The Reliability Coordinator shall disseminate information within its Reliability Coordinator Area, as required.
- R5.** Each Reliability Coordinator shall monitor system frequency and its Balancing Authorities' performance and direct any necessary rebalancing to return to CPS and DCS compliance. The Transmission Operators and Balancing Authorities shall utilize all resources, including firm load shedding, as directed by its Reliability Coordinator to relieve the emergent condition.
- R6.** The Reliability Coordinator shall coordinate with Transmission Operators, Balancing Authorities, and Generator Operators as needed to develop and implement action plans to mitigate potential or actual SOL, CPS, or DCS violations. The Reliability Coordinator shall coordinate pending generation and transmission maintenance outages with Transmission Operators, Balancing Authorities, and Generator Operators as needed in both the real time and next-day reliability analysis timeframes.
- R7.** As necessary, the Reliability Coordinator shall assist the Balancing Authorities in its Reliability Coordinator Area in arranging for assistance from neighboring Reliability Coordinator Areas or Balancing Authorities.
- R8.** The Reliability Coordinator shall identify sources of large Area Control Errors that may be contributing to Frequency Error, Time Error, or Inadvertent Interchange and shall discuss corrective actions with the appropriate Balancing Authority. The Reliability Coordinator shall direct its Balancing Authority to comply with CPS and DCS.
- R9.** Whenever a Special Protection System that may have an inter-Balancing Authority, or inter-Transmission Operator impact (e.g., could potentially affect transmission flows resulting in a SOL or IROL violation) is armed, the Reliability Coordinators shall be aware of the impact of the operation of that Special Protection System on inter-area flows. The Transmission Operator shall immediately inform the Reliability Coordinator of the status of the Special Protection System including any degradation or potential failure to operate as expected.
- R10.** In instances where there is a difference in derived limits, the Transmission Operators, Balancing Authorities, Generator Operators, Transmission Service Providers, Load-Serving Entities, and Purchasing-Selling Entities shall always operate the Bulk Electric System to the most limiting parameter.
- R11.** The Transmission Service Provider shall respect SOLs and IROLs in accordance with filed tariffs and regional Total Transfer Calculation and Available Transfer Calculation processes.

- R12.** Each Reliability Coordinator who foresees a transmission problem (such as an SOL or IROL violation, loss of reactive reserves, etc.) within its Reliability Coordinator Area shall issue an alert to all impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area without delay. The receiving Reliability Coordinator shall disseminate this information to its impacted Transmission Operators and Balancing Authorities. The Reliability Coordinator shall notify all impacted Transmission Operators, Balancing Authorities, when the transmission problem has been mitigated.

C. Measures

- M1.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, Energy Management System description documents, computer printouts, a prepared report specifically detailing compliance to each of the bullets in Requirement 1, EMS availability, SCADA data collection system communications performance or equivalent evidence that will be used to confirm that it monitors the Reliability Coordinator Area parameters specified in Requirements 1.1 through 1.9.
- M2.** If one of its Balancing Authorities has insufficient operating reserves, the Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to computer printouts, operating logs, voice recordings or transcripts of voice recordings, or equivalent evidence that will be used to determine if the Reliability Coordinator directed and, if needed, assisted the Balancing Authorities in the Reliability Coordinator Area to arrange for assistance from neighboring Balancing Authorities. (Requirement 2 and Requirement 7)
- M3.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to determine if it informed Transmission Operators and Balancing Authorities of Geo-Magnetic Disturbance (GMD) forecast information and provided assistance as needed in the development of any required response plans. (Requirement 3)
- M4.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, Hot Line recordings, electronic communications or equivalent evidence that will be used to determine if it disseminated information within its Reliability Coordinator Area in accordance with Requirement 4.
- M5.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, computer printouts, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that it monitored system frequency and Balancing Authority performance and directed any necessary rebalancing, as specified in Requirement 5 Part 1.
- M6.** The Transmission Operators and Balancing Authorities shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that it utilized all resources, including firm load shedding, as directed by its Reliability Coordinator, to relieve an emergent condition. (Requirement 5 Part 2)
- M7.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, voice recordings or transcripts of voice recordings, electronic communications, operator logs or equivalent evidence that will be used to determine if it coordinated with Transmission Operators, Balancing Authorities, and Generator Operators as needed to develop and implement action plans to mitigate potential or actual SOL, CPS, or DCS violations including the coordination of pending generation and transmission maintenance

outages with Transmission Operators, Balancing Authorities and Generator Operators. (Requirement 6 Part 1)

- M8.** If a large Area Control Error has occurred, the Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, Hot Line recordings, electronic communications or equivalent evidence that will be used to determine if it identified sources of the Area Control Errors, and initiated corrective actions with the appropriate Balancing Authority if the problem was within the Reliability Coordinator's Area (Requirement 8 Part 1)
- M9.** If a Special Protection System is armed and that system could have had an inter-area impact, the Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, agreements with their Transmission Operators, procedural documents, operator logs, computer analysis, training modules, training records or equivalent evidence that will be used to confirm that it was aware of the impact of that Special Protection System on inter-area flows. (Requirement 9)
- M10.** If there is an instance where there is a disagreement on a derived limit, the Transmission Operator, Balancing Authority, Generator Operator, Load-serving Entity, Purchasing-selling Entity and Transmission Service Provider involved in the disagreement shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings, electronic communications or equivalent evidence that will be used to determine if it operated to the most limiting parameter. (Part 2 of Requirement 10)
- M11.** The Transmission Service Providers shall have and provide upon request evidence that could include, but is not limited to, procedural documents, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that it respected the SOLs or IROLs in accordance with filed tariffs and regional Total Transfer Calculation and Available Transfer Calculation processes. (Requirement 11 Part 2)
- M12.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that it issued alerts when it foresaw a transmission problem (such as an SOL or IROL violation, loss of reactive reserves, etc.) within its Reliability Coordinator Area, to all impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area as specified in Requirement 12 Part 1.
- M13.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that upon receiving information such as an SOL or IROL violation, loss of reactive reserves, etc. it disseminated the information to its impacted Transmission Operators and Balancing Authorities as specified in Requirement 12 Part 2.
- M14.** The Reliability Coordinator shall have and provide upon request evidence that could include, but is not limited to, operator logs, voice recordings or transcripts of voice recordings, electronic communications or equivalent evidence that will be used to confirm that it notified all impacted Transmission Operators, Balancing Authorities and Reliability Coordinators when a transmission problem has been mitigated. (Requirement 12 Part 3)

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

Regional Reliability Organizations shall be responsible for compliance monitoring.

1.2. Compliance Monitoring and Reset Time Frame

One or more of the following methods will be used to assess compliance:

- Self-certification (Conducted annually with submission according to schedule.)
- Spot Check Audits (Conducted anytime with up to 30 days notice given to prepare.)
- Periodic Audit (Conducted once every three years according to schedule.)
- Triggered Investigations (Notification of an investigation must be made within 60 days of an event or complaint of noncompliance. The entity will have up to 30 days to prepare for the investigation. An entity may request an extension of the preparation period and the extension will be considered by the Compliance Monitor on a case-by-case basis.)

The Performance-Reset Period shall be 12 months from the last finding of non-compliance.

1.3. Data Retention

For Measures 1 and 9, each Reliability Coordinator shall have its current in-force documents as evidence.

For Measures 2–8 and Measures 12 through 13, the Reliability Coordinator shall keep 90 days of historical data (evidence).

For Measure 6, the Transmission Operator and Balancing Authority shall keep 90 days of historical data (evidence).

For Measure 10, the Transmission Operator, Balancing Authority, and Transmission Service Provider shall keep 90 days of historical data (evidence).

For Measure 11, the Transmission Service Provider shall keep 90 days of historical data (evidence).

If an entity is found non-compliant the entity shall keep information related to the noncompliance until found compliant or for two years plus the current year, whichever is longer.

Evidence used as part of a triggered investigation shall be retained by the entity being investigated for one year from the date that the investigation is closed, as determined by the Compliance Monitor,

The Compliance Monitor shall keep the last periodic audit report and all requested and submitted subsequent compliance records.

1.4. Additional Compliance Information

None.

2. Violation Severity Levels:

Requirement	Lower	Moderate	High	Severe
R1	The Reliability Coordinator failed to monitor one (1) of the elements listed in IRO-005-1 R1.1 through R1.10.	The Reliability Coordinator failed to monitor two (2) of the elements listed in IRO-005-1 R1.1 through R1.10.	The Reliability Coordinator failed to monitor three (3) of the elements listed in IRO-005-1 R1.1 through R1.10.	The Reliability Coordinator failed to monitor more than three (3) of the elements listed in IRO-005-1 R1.1 through R1.10.
R1.1	The Reliability Coordinator failed to monitor the current status of Bulk Electric System elements (transmission or generation including critical auxiliaries such as Automatic Voltage Regulators and Special Protection Systems) and system loading.	N/A	N/A	N/A
R1.2	The Reliability Coordinator failed to monitor current pre-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan’s viability and scope.	N/A	N/A	N/A

Requirement	Lower	Moderate	High	Severe
R1.3	The Reliability Coordinator failed to monitor current post-contingency element conditions (voltage, thermal, or stability), including any applicable mitigation plans to alleviate SOL or IROL violations, including the plan's viability and scope.	N/A	N/A	N/A
R1.4	The Reliability Coordinator failed to monitor system real and reactive reserves (actual versus required).	N/A	N/A	N/A
R1.5	The Reliability Coordinator failed to monitor capacity and energy adequacy conditions.	N/A	N/A	N/A
R1.6	The Reliability Coordinator failed to monitor current ACE for all its Balancing Authorities.	N/A	N/A	N/A
R1.7	The Reliability Coordinator failed to monitor current local or Transmission Loading Relief procedures in effect.	N/A	N/A	N/A
R1.8	The Reliability Coordinator failed to monitor planned generation dispatches.	N/A	N/A	N/A
R1.9	The Reliability Coordinator failed to monitor planned transmission or generation outages.	N/A	N/A	N/A

Requirement	Lower	Moderate	High	Severe
R1.10	The Reliability Coordinator failed to monitor contingency events.	N/A	N/A	N/A
R2	N/A	The Reliability Coordinator failed to direct the Balancing Authorities in the Reliability Coordinator Area to arrange for assistance from neighboring Balancing Authorities.	The Reliability Coordinator failed to issue Energy Emergency Alerts as needed and at the request of its Balancing Authorities and Load-Serving Entities.	The Reliability Coordinator failed to monitor its Balancing Authorities' parameters to ensure that the required amount of operating reserves was provided and available as required to meet the Control Performance Standard and Disturbance Control Standard requirements.
R3	N/A	N/A	The Reliability Coordinator ensured its Transmission Operators and Balancing Authorities were aware of Geo-Magnetic Disturbance (GMD) forecast information, but failed to assist, when needed, in the development of any required response plans.	The Reliability Coordinator failed to ensure its Transmission Operators and Balancing Authorities were aware of Geo-Magnetic Disturbance (GMD) forecast information.
R4	N/A	N/A	N/A	The Reliability Coordinator failed to disseminate information within its Reliability Coordinator Area, when required.

Requirement	Lower	Moderate	High	Severe
R5	N/A	N/A	The Reliability Coordinator monitored system frequency and its Balancing Authorities' performance but failed to direct any necessary rebalancing to return to CPS and DCS compliance.	The Reliability Coordinator failed to monitor system frequency and its Balancing Authorities' performance and direct any necessary rebalancing to return to CPS and DCS compliance or the responsible entity failed to utilize all resources, including firm load shedding, as directed by its Reliability Coordinator to relieve the emergent condition.

Requirement	Lower	Moderate	High	Severe
R6	N/A	<p>The Reliability Coordinator coordinated with Transmission Operators, Balancing Authorities, and Generator Operators, as needed, to develop action plans to mitigate potential or actual SOL, CPS, or DCS violations but failed to implement said plans, or the Reliability Coordinator coordinated pending generation and transmission maintenance outages with Transmission Operators, Balancing Authorities, and Generator Operators as needed in the real-time reliability analysis timeframe but failed to coordinate pending generation and transmission maintenance outages in the next-day reliability analysis timeframe.</p>	<p>The Reliability Coordinator failed to coordinate with Transmission Operators, Balancing Authorities, and Generator Operators as needed to develop and implement action plans to mitigate potential or actual SOL, CPS, or DCS violations, or the Reliability Coordinator failed to coordinate pending generation and transmission maintenance outages with Transmission Operators, Balancing Authorities, and Generator Operators as needed in both the real-time and next-day reliability analysis timeframes.</p>	<p>The Reliability Coordinator failed to coordinate with Transmission Operators, Balancing Authorities, and Generator Operators as needed to develop and implement action plans to mitigate potential or actual SOL, CPS, or DCS violations and the Reliability Coordinator failed to coordinate pending generation and transmission maintenance outages with Transmission Operators, Balancing Authorities, and Generator Operators as needed in both the real-time and next-day reliability analysis timeframes.</p>
R7	N/A	N/A	N/A	<p>The Reliability Coordinator failed to assist the Balancing Authorities in its Reliability Coordinator Area in arranging for assistance from neighboring Reliability Coordinator Areas or Balancing Authorities, when necessary.</p>

Requirement	Lower	Moderate	High	Severe
R8	N/A	The Reliability Coordinator identified sources of large Area Control Errors that were contributing to Frequency Error, Time Error, or Inadvertent Interchange and discussed corrective actions with the appropriate Balancing Authority but failed to direct the Balancing Authority to comply with CPS and DCS.	The Reliability Coordinator identified sources of large Area Control Errors that were contributing to Frequency Error, Time Error, or Inadvertent Interchange but failed to discuss corrective actions with the appropriate Balancing Authority.	The Reliability Coordinator failed to identify sources of large Area Control Errors that were contributing to Frequency Error, Time Error, or Inadvertent Interchange.
R9	N/A	N/A	N/A	The Reliability Coordinator failed to be aware of the impact on inter-area flows of an inter-Balancing Authority or inter-Transmission Operator, following the operation of a Special Protection System that is armed (e.g., could potentially affect transmission flows resulting in a SOL or IROL violation), or the Transmission Operator failed to immediately inform the Reliability Coordinator of the status of the Special Protection System including any degradation or potential failure to operate as expected.

Requirement	Lower	Moderate	High	Severe
R10	N/A	N/A	N/A	The responsible entity failed to operate the Bulk Electric System to the most limiting parameter in instances where there was a difference in derived limits.
R11	N/A	N/A	N/A	The Transmission Service Provider failed to respect SOLs or IROLs in accordance with filed tariffs and regional Total Transfer Calculation and Available Transfer Calculation processes.
R12	N/A	The Reliability Coordinator failed to notify all impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated.	N/A	The Reliability Coordinator who foresaw a transmission problem (such as an SOL or IROL violation, loss of reactive reserves, etc.) within its Reliability Coordinator Area failed to issue an alert to all impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area, or the receiving Reliability Coordinator failed to disseminate this information to its impacted Transmission Operators and Balancing Authorities.

E. Regional Differences

None identified.

Version History

Version	Date	Action	Change Tracking
0	April 1, 2005	Effective Date	New
0	August 8, 2005	Removed “Proposed” from Effective Date	Errata
1		Retired R2, R3, R5; modified R9, R13 and R14; retired R16 and R17 Retired M2 and M3; modified M9 and M12; retired M13 Made conforming changes to data retention Replaced Levels of Non-compliance with the Feb 28, BOT approved Violation Severity Levels (VSLs) Retired VSLs associated with R2, R3, R5, R16 and R17; Modified VSLs associated with R9 and R13, and R14	Revised
2	November 1, 2006	Approved by the Board of Trustees	
2	January 1, 2007	Effective Date	
2a	November 5, 2009	Approved by the Board of Trustees	
3	October 17, 2008	Approved by the Board of Trustees	
3	March 23, 2011	Order issued by FERC approving IRO-005-3 (approval effective 5/23/11)	