

A. Introduction

1. **Title:** System Protection Coordination

2. **Number:** PRC-001-1

3. **Purpose:**

To ensure system protection is coordinated among operating entities.

4. **Applicability**

4.1. Balancing Authorities

4.2. Transmission Operators

4.3. Generator Operators

5. **Effective Date:** January 1, 2007

B. Requirements

R1. Each Transmission Operator, Balancing Authority, and Generator Operator shall be familiar with the purpose and limitations of protection system schemes applied in its area.

R2. Each Generator Operator and Transmission Operator shall notify reliability entities of relay or equipment failures as follows:

R2.1. If a protective relay or equipment failure reduces system reliability, the Generator Operator shall notify its Transmission Operator and Host Balancing Authority. The Generator Operator shall take corrective action as soon as possible.

R2.2. If a protective relay or equipment failure reduces system reliability, the Transmission Operator shall notify its Reliability Coordinator and affected Transmission Operators and Balancing Authorities. The Transmission Operator shall take corrective action as soon as possible.

R3. A Generator Operator or Transmission Operator shall coordinate new protective systems and changes as follows.

R3.1. Each Generator Operator shall coordinate all new protective systems and all protective system changes with its Transmission Operator and Host Balancing Authority.

R3.2. Each Transmission Operator shall coordinate all new protective systems and all protective system changes with neighboring Transmission Operators and Balancing Authorities.

R4. Each Transmission Operator shall coordinate protection systems on major transmission lines and interconnections with neighboring Generator Operators, Transmission Operators, and Balancing Authorities.

R5. A Generator Operator or Transmission Operator shall coordinate changes in generation, transmission, load or operating conditions that could require changes in the protection systems of others:

- R5.1.** Each Generator Operator shall notify its Transmission Operator in advance of changes in generation or operating conditions that could require changes in the Transmission Operator's protection systems.
- R5.2.** Each Transmission Operator shall notify neighboring Transmission Operators in advance of changes in generation, transmission, load, or operating conditions that could require changes in the other Transmission Operators' protection systems.
- R6.** Each Transmission Operator and Balancing Authority shall monitor the status of each Special Protection System in their area, and shall notify affected Transmission Operators and Balancing Authorities of each change in status.

C. Measures

- M1.** Each Generator Operator and Transmission Operator shall have and provide upon request evidence that could include but is not limited to, revised fault analysis study, letters of agreement on settings, notifications of changes, or other equivalent evidence that will be used to confirm that there was coordination of new protective systems or changes as noted in Requirements 3, 3.1, and 3.2.
- M2.** Each Transmission Operator and Balancing Authority shall have and provide upon request evidence that could include but is not limited to, documentation, electronic logs, computer printouts, or computer demonstration or other equivalent evidence that will be used to confirm that it monitors the Special Protection Systems in its area. (Requirement 6 Part 1)
- M3.** Each Transmission Operator and Balancing Authority shall have and provide upon request evidence that could include but is not limited to, operator logs, phone records, electronic-notifications or other equivalent evidence that will be used to confirm that it notified affected Transmission Operator and Balancing Authorities of changes in status of one of its Special Protection Systems. (Requirement 6 Part 2)

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

Regional Reliability Organizations shall be responsible for compliance monitoring.

1.2. Compliance Monitoring and Reset Time Frame

One or more of the following methods will be used to assess compliance:

- Self-certification (Conducted annually with submission according to schedule.)
- Spot Check Audits (Conducted anytime with up to 30 days notice given to prepare.)
- Periodic Audit (Conducted once every three years according to schedule.)
- Triggered Investigations (Notification of an investigation must be made within 60 days of an event or complaint of noncompliance. The entity will

have up to 30 days to prepare for the investigation. An entity may request an extension of the preparation period and the extension will be considered by the Compliance Monitor on a case-by-case basis.)

The Performance-Reset Period shall be 12 months from the last finding of non-compliance.

1.3. Data Retention

Each Generator Operator and Transmission Operator shall have current, in-force documents available as evidence of compliance for Measure 1.

Each Transmission Operator and Balancing Authority shall keep 90 days of historical data (evidence) for Measures 2 and 3.

If an entity is found non-compliant the entity shall keep information related to the noncompliance until found compliant or for two years plus the current year, whichever is longer.

Evidence used as part of a triggered investigation shall be retained by the entity being investigated for one year from the date that the investigation is closed, as determined by the Compliance Monitor,

The Compliance Monitor shall keep the last periodic audit report and all requested and submitted subsequent compliance records.

1.4. Additional Compliance Information

None.

2. Levels of Non-Compliance for Generator Operators:

2.1. Level 1: Not applicable.

2.2. Level 2: Not applicable.

2.3. Level 3: Not applicable.

2.4. Level 4: Failed to provide evidence of coordination when installing new protective systems and all protective system changes with its Transmission Operator and Host Balancing Authority as specified in R3.1.

3. Levels of Non-Compliance for Transmission Operators:

3.1. Level 1: Not applicable.

3.2. Level 2: Not applicable.

3.3. Level 3: Not applicable.

3.4. Level 4: There shall be a separate Level 4 non-compliance, for every one of the following requirements that is in violation:

3.4.1 Failed to provide evidence of coordination when installing new protective systems and all protective system changes with neighboring Transmission Operators and Balancing Authorities as specified in R3.2.

3.4.2 Did not monitor the status of each Special Protection System, or did not notify affected Transmission Operators, Balancing Authorities of changes in special protection status as specified in R6.

4. Levels of Non-Compliance for Balancing Authorities:

4.1. Level 1: Not applicable.

4.2. Level 2: Not applicable.

4.3. Level 3: Not applicable.

4.4. Level 4: Did not monitor the status of each Special Protection System, or did not notify affected Transmission Operators, Balancing Authorities of changes in special protection status as specified in R6.

E. Regional Differences

None identified.

Version History

Version	Date	Action	Change Tracking
0	April 1, 2005	Effective Date	New
0	August 8, 2005	Removed “Proposed” from Effective Date	Errata
0	August 25, 2005	Fixed Standard number in Introduction from PRC-001-1 to PRC-001-0	Errata
1	November 1, 2006	Adopted by Board of Trustees	Revised