

**A. Introduction**

- 1. Title:** Protection System Maintenance
- 2. Number:** PRC-005-2
- 3. Purpose:** To document and implement programs for the maintenance of all Protection Systems affecting the reliability of the Bulk Electric System (BES) so that these Protection Systems are kept in working order.
- 4. Applicability:**
  - 4.1. Functional Entities:**
    - 4.1.1** Transmission Owner
    - 4.1.2** Generator Owner
    - 4.1.3** Distribution Provider
  - 4.2. Facilities:**
    - 4.2.1** Protection Systems that are installed for the purpose of detecting Faults on BES Elements (lines, buses, transformers, etc.)
    - 4.2.2** Protection Systems used for underfrequency load-shedding systems installed per ERO underfrequency load-shedding requirements.
    - 4.2.3** Protection Systems used for undervoltage load-shedding systems installed to prevent system voltage collapse or voltage instability for BES reliability.
    - 4.2.4** Protection Systems installed as a Special Protection System (SPS) for BES reliability.
    - 4.2.5** Protection Systems for generator Facilities that are part of the BES, including:
      - 4.2.5.1** Protection Systems that act to trip the generator either directly or via lockout or auxiliary tripping relays.
      - 4.2.5.2** Protection Systems for generator step-up transformers for generators that are part of the BES.
      - 4.2.5.3** Protection Systems for transformers connecting aggregated generation, where the aggregated generation is part of the BES (e.g., transformers connecting facilities such as wind-farms to the BES).
      - 4.2.5.4** Protection Systems for station service or excitation transformers connected to the generator bus of generators which are part of the BES, that act to trip the generator either directly or via lockout or tripping auxiliary relays.
- 5. Effective Date:** See Implementation Plan

**B. Requirements**

- R1.** Each Transmission Owner, Generator Owner, and Distribution Provider shall establish a Protection System Maintenance Program (PSMP) for its Protection Systems identified in Section 4.2. [*Violation Risk Factor: Medium*] [*Time Horizon: Operations Planning*]

The PSMP shall:

- 1.1.** Identify which maintenance method (time-based, performance-based per PRC-005 Attachment A, or a combination) is used to address each Protection System Component Type. All batteries associated with the station dc supply Component Type of a Protection System shall be included in a time-based program as described in Table 1-4 and Table 3.
- 1.2.** Include the applicable monitored Component attributes applied to each Protection System Component Type consistent with the maintenance intervals specified in Tables 1-1 through 1-5, Table 2, and Table 3 where monitoring is used to extend the maintenance intervals beyond those specified for unmonitored Protection System Components.
- R2.** Each Transmission Owner, Generator Owner, and Distribution Provider that uses performance-based maintenance intervals in its PSMP shall follow the procedure established in PRC-005 Attachment A to establish and maintain its performance-based intervals. *[Violation Risk Factor: Medium] [Time Horizon: Operations Planning]*
- R3.** Each Transmission Owner, Generator Owner, and Distribution Provider that utilizes time-based maintenance program(s) shall maintain its Protection System Components that are included within the time-based maintenance program in accordance with the minimum maintenance activities and maximum maintenance intervals prescribed within Tables 1-1 through 1-5, Table 2, and Table 3. *[Violation Risk Factor: High] [Time Horizon: Operations Planning]*
- R4.** Each Transmission Owner, Generator Owner, and Distribution Provider that utilizes performance-based maintenance program(s) in accordance with Requirement R2 shall implement and follow its PSMP for its Protection System Components that are included within the performance-based program(s). *[Violation Risk Factor: High] [Time Horizon: Operations Planning]*
- R5.** Each Transmission Owner, Generator Owner, and Distribution Provider shall demonstrate efforts to correct identified Unresolved Maintenance Issues. *[Violation Risk Factor: Medium] [Time Horizon: Operations Planning]*

**Component Type** - Any one of the five specific elements of the Protection System definition.

**Component** – A component is any individual discrete piece of equipment included in a Protection System, including but not limited to a protective relay or current sensing device. The designation of what constitutes a control circuit component is very dependent upon how an entity performs and tracks the testing of the control circuitry. Some entities test their control circuits on a breaker basis whereas others test their circuitry on a local zone of protection basis. Thus, entities are allowed the latitude to designate their own definitions of control circuit components. Another example of where the entity has some discretion on determining what constitutes a single component is the voltage and current sensing devices, where the entity may choose either to designate a full three-phase set of such devices or a single device as a single component.

**Unresolved Maintenance Issue** - A deficiency identified during a maintenance activity that causes the component to not meet the intended performance, cannot be corrected during the maintenance interval, and requires follow-up corrective action.

**C. Measures**

- M1.** Each Transmission Owner, Generator Owner and Distribution Provider shall have a documented Protection System Maintenance Program in accordance with Requirement R1.

For each Protection System Component Type, the documentation shall include the type of maintenance method applied (time-based, performance-based, or a combination of these maintenance methods), and shall include all batteries associated with the station dc supply Component Types in a time-based program as described in Table 1-4 and Table 3. (Part 1.1)

For Component Types that use monitoring to extend the maintenance intervals, the responsible entity(s) shall have evidence for each protection Component Type (such as manufacturer’s specifications or engineering drawings) of the appropriate monitored Component attributes as specified in Tables 1-1 through 1-5, Table 2, and Table 3. (Part 1.2)
- M2.** Each Transmission Owner, Generator Owner, and Distribution Provider that uses performance-based maintenance intervals shall have evidence that its current performance-based maintenance program(s) is in accordance with Requirement R2, which may include but is not limited to Component lists, dated maintenance records, and dated analysis records and results.
- M3.** Each Transmission Owner, Generator Owner, and Distribution Provider that utilizes time-based maintenance program(s) shall have evidence that it has maintained its Protection System Components included within its time-based program in accordance with Requirement R3. The evidence may include but is not limited to dated maintenance records, dated maintenance summaries, dated check-off lists, dated inspection records, or dated work orders.
- M4.** Each Transmission Owner, Generator Owner, and Distribution Provider that utilizes performance-based maintenance intervals in accordance with Requirement R2 shall have evidence that it has implemented the Protection System Maintenance Program for the Protection System Components included in its performance-based program in accordance with Requirement R4. The evidence may include but is not limited to dated maintenance records, dated maintenance summaries, dated check-off lists, dated inspection records, or dated work orders.
- M5.** Each Transmission Owner, Generator Owner, and Distribution Provider shall have evidence that it has undertaken efforts to correct identified Unresolved Maintenance Issues in accordance with Requirement R5. The evidence may include but is not limited to work orders, replacement Component orders, invoices, project schedules with completed milestones, return material authorizations (RMAs) or purchase orders.

**D. Compliance**

- 1. Compliance Monitoring Process**

  - 1.1. Compliance Enforcement Authority**

    - Regional Entity
  - 1.2. Compliance Monitoring and Enforcement Processes:**

    - Compliance Audit
    - Self-Certification
    - Spot Checking
    - Compliance Investigation
    - Self-Reporting
    - Complaint

**1.3. Evidence Retention**

The following evidence retention periods identify the period of time an entity is required to retain specific evidence to demonstrate compliance. For instances where the evidence retention period specified below is shorter than the time since the last audit, the Compliance Enforcement Authority may ask an entity to provide other evidence to show that it was compliant for the full time period since the last audit.

The Transmission Owner, Generator Owner, and Distribution Provider shall each keep data or evidence to show compliance as identified below unless directed by its Compliance Enforcement Authority to retain specific evidence for a longer period of time as part of an investigation.

For Requirement R1, the Transmission Owner, Generator Owner, and Distribution Provider shall each keep its current dated Protection System Maintenance Program, as well as any superseded versions since the preceding compliance audit, including the documentation that specifies the type of maintenance program applied for each Protection System Component Type.

For Requirement R2, Requirement R3, Requirement R4, and Requirement R5, the Transmission Owner, Generator Owner, and Distribution Provider shall each keep documentation of the two most recent performances of each distinct maintenance activity for the Protection System Component, or all performances of each distinct maintenance activity for the Protection System Component since the previous scheduled audit date, whichever is longer.

The Compliance Enforcement Authority shall keep the last audit records and all requested and submitted subsequent audit records.

**1.4. Additional Compliance Information**

None.

2. Violation Severity Levels

Requirement Number	Lower VSL	Moderate VSL	High VSL	Severe VSL
R1	The responsible entity’s PSMP failed to specify whether one Component Type is being addressed by time-based or performance-based maintenance, or a combination of both. (Part 1.1)	The responsible entity’s PSMP failed to specify whether two Component Types are being addressed by time-based or performance-based maintenance, or a combination of both. (Part 1.1)	The responsible entity’s PSMP failed to include the applicable monitoring attributes applied to each Protection System Component Type consistent with the maintenance intervals specified in Tables 1-1 through 1-5, Table 2, and Table 3 where monitoring is used to extend the maintenance intervals beyond those specified for unmonitored Protection System Components. (Part 1.2).	<p>The responsible entity failed to establish a PSMP.</p> <p style="text-align: center;">OR</p> <p>The responsible entity failed to specify whether three or more Component Types are being addressed by time-based or performance-based maintenance, or a combination of both. (Part 1.1).</p> <p style="text-align: center;">OR</p> <p>The responsible entity’s PSMP failed to include applicable station batteries in a time-based program. (Part 1.1)</p>
R2	The responsible entity uses performance-based maintenance intervals in its PSMP but failed to reduce Countable Events to no more than 4% within three years.	NA	The responsible entity uses performance-based maintenance intervals in its PSMP but failed to reduce Countable Events to no more than 4% within four years.	<p>The responsible entity uses performance-based maintenance intervals in its PSMP but:</p> <ol style="list-style-type: none"> <li>1) Failed to establish the technical justification described within Requirement R2 for the initial use of the performance-based PSMP</li> </ol> <p style="text-align: center;">OR</p> <ol style="list-style-type: none"> <li>2) Failed to reduce Countable Events to no more than 4% within five years</li> </ol> <p style="text-align: center;">OR</p> <ol style="list-style-type: none"> <li>3) Maintained a Segment with less than 60 Components</li> </ol> <p style="text-align: center;">OR</p> <ol style="list-style-type: none"> <li>4) Failed to:</li> </ol>

**Standard PRC-005-2 — Protection System Maintenance**

Requirement Number	Lower VSL	Moderate VSL	High VSL	Severe VSL
				<ul style="list-style-type: none"> <li>• Annually update the list of Components, OR</li> <li>• Annually perform maintenance on the greater of 5% of the segment population or 3 Components, OR</li> <li>• Annually analyze the program activities and results for each Segment.</li> </ul>
R3	For Protection System Components included within a time-based maintenance program, the responsible entity failed to maintain 5% or less of the total Components included within a specific Protection System Component Type, in accordance with the minimum maintenance activities and maximum maintenance intervals prescribed within Tables 1-1 through 1-5, Table 2, and Table 3.	For Protection System Components included within a time-based maintenance program, the responsible entity failed to maintain more than 5% but 10% or less of the total Components included within a specific Protection System Component Type, in accordance with the minimum maintenance activities and maximum maintenance intervals prescribed within Tables 1-1 through 1-5, Table 2, and Table 3.	For Protection System Components included within a time-based maintenance program, the responsible entity failed to maintain more than 10% but 15% or less of the total Components included within a specific Protection System Component Type, in accordance with the minimum maintenance activities and maximum maintenance intervals prescribed within Tables 1-1 through 1-5, Table 2, and Table 3.	For Protection System Components included within a time-based maintenance program, the responsible entity failed to maintain more than 15% of the total Components included within a specific Protection System Component Type, in accordance with the minimum maintenance activities and maximum maintenance intervals prescribed within Tables 1-1 through 1-5, Table 2, and Table 3.
R4	For Protection System Components included within a performance-based maintenance program, the responsible entity failed to maintain 5% or less of the annual scheduled maintenance for a specific Protection System Component Type in accordance with their performance-based PSMP.	For Protection System Components included within a performance-based maintenance program, the responsible entity failed to maintain more than 5% but 10% or less of the annual scheduled maintenance for a specific Protection System Component Type in accordance with their performance-based PSMP.	For Protection System Components included within a performance-based maintenance program, the responsible entity failed to maintain more than 10% but 15% or less of the annual scheduled maintenance for a specific Protection System Component Type in accordance with their performance-based PSMP.	For Protection System Components included within a performance-based maintenance program, the responsible entity failed to maintain more than 15% of the annual scheduled maintenance for a specific Protection System Component Type in accordance with their performance-based PSMP.

**Standard PRC-005-2 — Protection System Maintenance**

---

Requirement Number	Lower VSL	Moderate VSL	High VSL	Severe VSL
R5	The responsible entity failed to undertake efforts to correct 5 or fewer identified Unresolved Maintenance Issues.	The responsible entity failed to undertake efforts to correct greater than 5, but less than or equal to 10 identified Unresolved Maintenance Issues.	The responsible entity failed to undertake efforts to correct greater than 10, but less than or equal to 15 identified Unresolved Maintenance Issues.	The responsible entity failed to undertake efforts to correct greater than 15 identified Unresolved Maintenance Issues.

**E. Regional Variances**

None

**F. Supplemental Reference Document**

The following documents present a detailed discussion about determination of maintenance intervals and other useful information regarding establishment of a maintenance program.

1. PRC-005-2 Protection System Maintenance Supplementary Reference and FAQ — July 2012.

**Version History**

<b>Version</b>	<b>Date</b>	<b>Action</b>	<b>Change Tracking</b>
0	April 1, 2005	Effective Date	New
1	December 1, 2005	<ol style="list-style-type: none"> <li>1. Changed incorrect use of certain hyphens (-) to “en dash” (–) and “em dash (—).”</li> <li>2. Added “periods” to items where appropriate.</li> <li>3. Changed “Timeframe” to “Time Frame” in item D, 1.2.</li> </ol>	01/20/05
1a	February 17, 2011	Added Appendix 1 - Interpretation regarding applicability of standard to protection of radially connected transformers	Project 2009-17 interpretation
1a	February 17, 2011	Adopted by Board of Trustees	
1a	September 26, 2011	FERC Order issued approving interpretation of R1 and R2 (FERC’s Order is effective as of September 26, 2011)	
1.1a	February 1, 2012	Errata change: Clarified inclusion of generator interconnection Facility in Generator Owner’s responsibility	Revision under Project 2010-07
1b	February 3, 2012	FERC Order issued approving interpretation of R1, R1.1, and R1.2 (FERC’s Order dated March 14, 2012). Updated version from 1a to 1b.	Project 2009-10 Interpretation
1.1b	April 23, 2012	Updated standard version to 1.1b to reflect FERC approval of PRC-005-1b.	Revision under Project 2010-07



**Standard PRC-005-2 – Protection System Maintenance**

1.1b	May 9, 2012	PRC-005-1.1b was adopted by the Board of Trustees as part of Project 2010-07 (GOTO).	
2	November 7, 2012	Adopted by Board of Trustees	Complete revision, absorbing maintenance requirements from PRC-005-1b, PRC-008-0, PRC-011-0, PRC-017-0
2	October 17, 2013	Errata Change: The Standards Committee approved an errata change to the implementation plan for PRC-005-2 to add the phrase “or as otherwise made effective pursuant to the laws applicable to such ERO governmental authorities;” to the second sentence under the “Retirement of Existing Standards” section.	
2	December 19, 2013	FERC Order issued approving PRC-005-2. (The enforcement date for PRC-005-2 will be April 1, 2015, which is the first date entities must be compliant with part of the standard. The implementation plan for PRC-005-2 includes specific compliance dates and timeframes for each of the Requirements. The regulatory approval date in the U.S. is February 24, 2014.	
2	May 7, 2014	Adopted by the NERC Board of Trustees to modify VSLs for Requirement R1.	
2	August 25, 2014	FERC issued letter order to modify VSLs for Requirement R1.	

Table 1-1 Component Type - Protective Relay Excluding distributed UFLS and distributed UVLS (see Table 3)		
Component Attributes	Maximum Maintenance Interval <sup>1</sup>	Maintenance Activities
Any unmonitored protective relay not having all the monitoring attributes of a category below.	6 calendar years	For all unmonitored relays: <ul style="list-style-type: none"> <li>• Verify that settings are as specified</li> </ul> For non-microprocessor relays: <ul style="list-style-type: none"> <li>• Test and, if necessary calibrate</li> </ul> For microprocessor relays: <ul style="list-style-type: none"> <li>• Verify operation of the relay inputs and outputs that are essential to proper functioning of the Protection System.</li> <li>• Verify acceptable measurement of power system input values.</li> </ul>
Monitored microprocessor protective relay with the following: <ul style="list-style-type: none"> <li>• Internal self-diagnosis and alarming (see Table 2).</li> <li>• Voltage and/or current waveform sampling three or more times per power cycle, and conversion of samples to numeric values for measurement calculations by microprocessor electronics.</li> <li>• Alarming for power supply failure (see Table 2).</li> </ul>	12 calendar years	Verify: <ul style="list-style-type: none"> <li>• Settings are as specified.</li> <li>• Operation of the relay inputs and outputs that are essential to proper functioning of the Protection System.</li> <li>• Acceptable measurement of power system input values.</li> </ul>

<sup>1</sup> For the tables in this standard, a calendar year starts on the first day of a new year (January 1) after a maintenance activity has been completed. For the tables in this standard, a calendar month starts on the first day of the first month after a maintenance activity has been completed.

Table 1-1 Component Type - Protective Relay Excluding distributed UFLS and distributed UVLS (see Table 3)		
Component Attributes	Maximum Maintenance Interval <sup>1</sup>	Maintenance Activities
Monitored microprocessor protective relay with preceding row attributes and the following: <ul style="list-style-type: none"> <li>• Ac measurements are continuously verified by comparison to an independent ac measurement source, with alarming for excessive error (See Table 2).</li> <li>• Some or all binary or status inputs and control outputs are monitored by a process that continuously demonstrates ability to perform as designed, with alarming for failure (See Table 2).</li> <li>• Alarming for change of settings (See Table 2).</li> </ul>	12 calendar years	Verify only the unmonitored relay inputs and outputs that are essential to proper functioning of the Protection System.

Table 1-2 Component Type - Communications Systems Excluding distributed UFLS and distributed UVLS (see Table 3)		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any unmonitored communications system necessary for correct operation of protective functions, and not having all the monitoring attributes of a category below.	4 calendar months	Verify that the communications system is functional.
	6 calendar years	Verify that the communications system meets performance criteria pertinent to the communications technology applied (e.g. signal level, reflected power, or data error rate). Verify operation of communications system inputs and outputs that are essential to proper functioning of the Protection System.
Any communications system with continuous monitoring or periodic automated testing for the presence of the channel function, and alarming for loss of function (See Table 2).	12 calendar years	Verify that the communications system meets performance criteria pertinent to the communications technology applied (e.g. signal level, reflected power, or data error rate). Verify operation of communications system inputs and outputs that are essential to proper functioning of the Protection System.
Any communications system with all of the following: <ul style="list-style-type: none"> <li>• Continuous monitoring or periodic automated testing for the performance of the channel using criteria pertinent to the communications technology applied (e.g. signal level, reflected power, or data error rate, and alarming for excessive performance degradation). (See Table 2)</li> <li>• Some or all binary or status inputs and control outputs are monitored by a process that continuously demonstrates ability to perform as designed, with alarming for failure (See Table 2).</li> </ul>	12 calendar years	Verify only the unmonitored communications system inputs and outputs that are essential to proper functioning of the Protection System

Table 1-3 Component Type - Voltage and Current Sensing Devices Providing Inputs to Protective Relays Excluding distributed UFLS and distributed UVLS (see Table 3)		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any voltage and current sensing devices not having monitoring attributes of the category below.	12 calendar years	Verify that current and voltage signal values are provided to the protective relays.
Voltage and Current Sensing devices connected to microprocessor relays with AC measurements are continuously verified by comparison of sensing input value, as measured by the microprocessor relay, to an independent ac measurement source, with alarming for unacceptable error or failure (see Table 2).	No periodic maintenance specified	None.

**Table 1-4(a)**  
**Component Type – Protection System Station dc Supply Using Vented Lead-Acid (VLA) Batteries**  
**Excluding distributed UFLS and distributed UVLS (see Table 3)**

Protection System Station dc supply used only for non-BES interrupting devices for SPS, non-distributed UFLS systems, or non-distributed UVLS systems is excluded (see Table 1-4(e)).

Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Protection System Station dc supply using <b>Vented Lead-Acid (VLA) batteries</b> not having monitoring attributes of Table 1-4(f).	4 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Station dc supply voltage</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• Electrolyte level</li> <li>• For unintentional grounds</li> </ul>
	18 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Float voltage of battery charger</li> <li>• Battery continuity</li> <li>• Battery terminal connection resistance</li> <li>• Battery intercell or unit-to-unit connection resistance</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• Cell condition of all individual battery cells where cells are visible – or measure battery cell/unit internal ohmic values where the cells are not visible</li> <li>• Physical condition of battery rack</li> </ul>
	18 Calendar Months -or- 6 Calendar Years	Verify that the station battery can perform as manufactured by evaluating cell/unit measurements indicative of battery performance (e.g. internal ohmic values or float current) against the station battery baseline. -or- Verify that the station battery can perform as manufactured by conducting a performance or modified performance capacity test of the entire battery bank.



Table 1-4(b)

**Component Type – Protection System Station dc Supply Using Valve-Regulated Lead-Acid (VRLA) Batteries  
Excluding distributed UFLS and distributed UVLS (see Table 3)**

Protection System Station dc supply used only for non-BES interrupting devices for SPS, non-distributed UFLS systems, or non-distributed UVLS systems is excluded (see Table 1-4(e)).

Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Protection System Station dc supply <b>with Valve Regulated Lead-Acid (VRLA) batteries</b> not having monitoring attributes of Table 1-4(f).	4 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Station dc supply voltage</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• For unintentional grounds</li> </ul>
	6 Calendar Months	Inspect: <ul style="list-style-type: none"> <li>• Condition of all individual units by measuring battery cell/unit internal ohmic values.</li> </ul>
	18 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Float voltage of battery charger</li> <li>• Battery continuity</li> <li>• Battery terminal connection resistance</li> <li>• Battery intercell or unit-to-unit connection resistance</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• Physical condition of battery rack</li> </ul>
	6 Calendar Months -or- 3 Calendar Years	Verify that the station battery can perform as manufactured by evaluating cell/unit measurements indicative of battery performance (e.g. internal ohmic values or float current) against the station battery baseline. -or- Verify that the station battery can perform as manufactured by conducting a performance or modified performance capacity test of the entire battery bank.





Table 1-4(c) Component Type – Protection System Station dc Supply Using Nickel-Cadmium (NiCad) Batteries Excluding distributed UFLS and distributed UVLS (see Table 3)		
Protection System Station dc supply used only for non-BES interrupting devices for SPS, non-distributed UFLS system, or non-distributed UVLS systems is excluded (see Table 1-4(e)).		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Protection System Station dc supply <b>Nickel-Cadmium (NiCad) batteries</b> not having monitoring attributes of Table 1-4(f).	4 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Station dc supply voltage</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• Electrolyte level</li> <li>• For unintentional grounds</li> </ul>
	18 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Float voltage of battery charger</li> <li>• Battery continuity</li> <li>• Battery terminal connection resistance</li> <li>• Battery intercell or unit-to-unit connection resistance</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• Cell condition of all individual battery cells.</li> <li>• Physical condition of battery rack</li> </ul>
	6 Calendar Years	Verify that the station battery can perform as manufactured by conducting a performance or modified performance capacity test of the entire battery bank.

<b>Table 1-4(d)</b> <b>Component Type – Protection System Station dc Supply Using Non Battery Based Energy Storage</b> <b>Excluding distributed UFLS and distributed UVLS (see Table 3)</b>		
Protection System Station dc supply used only for non-BES interrupting devices for SPS, non-distributed UFLS system, or non-distributed UVLS systems is excluded (see Table 1-4(e)).		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any Protection System station dc supply not using a battery and not having monitoring attributes of Table 1-4(f).	4 Calendar Months	Verify: <ul style="list-style-type: none"> <li>• Station dc supply voltage</li> </ul> Inspect: <ul style="list-style-type: none"> <li>• For unintentional grounds</li> </ul>
	18 Calendar Months	Inspect: Condition of non-battery based dc supply
	6 Calendar Years	Verify that the dc supply can perform as manufactured when ac power is not present.

**Table 1-4(e)**

**Component Type – Protection System Station dc Supply for non-BES Interrupting Devices for SPS, non-distributed UFLS, and non-distributed UVLS systems**

Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any Protection System dc supply used for tripping only non-BES interrupting devices as part of a SPS, non-distributed UFLS, or non-distributed UVLS system and not having monitoring attributes of Table 1-4(f).	When control circuits are verified (See Table 1-5)	Verify Station dc supply voltage.

**Standard PRC-005-2 – Protection System Maintenance**

Table 1-4(f)		
Exclusions for Protection System Station dc Supply Monitoring Devices and Systems		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any station dc supply with high and low voltage monitoring and alarming of the battery charger voltage to detect charger overvoltage and charger failure (See Table 2).	No periodic maintenance specified	No periodic verification of station dc supply voltage is required.
Any battery based station dc supply with electrolyte level monitoring and alarming in every cell (See Table 2).		No periodic inspection of the electrolyte level for each cell is required.
Any station dc supply with unintentional dc ground monitoring and alarming (See Table 2).		No periodic inspection of unintentional dc grounds is required.
Any station dc supply with charger float voltage monitoring and alarming to ensure correct float voltage is being applied on the station dc supply (See Table 2).		No periodic verification of float voltage of battery charger is required.
Any battery based station dc supply with monitoring and alarming of battery string continuity (See Table 2).		No periodic verification of the battery continuity is required.
Any battery based station dc supply with monitoring and alarming of the intercell and/or terminal connection detail resistance of the entire battery (See Table 2).		No periodic verification of the intercell and terminal connection resistance is required.
Any Valve Regulated Lead-Acid (VRLA) or Vented Lead-Acid (VLA) station battery with internal ohmic value or float current monitoring and alarming, and evaluating present values relative to baseline internal ohmic values for every cell/unit (See Table 2).		No periodic evaluation relative to baseline of battery cell/unit measurements indicative of battery performance is required to verify the station battery can perform as manufactured.
Any Valve Regulated Lead-Acid (VRLA) or Vented Lead-Acid (VLA) station battery with monitoring and alarming of each cell/unit internal ohmic value (See Table 2).		No periodic inspection of the condition of all individual units by measuring battery cell/unit internal ohmic values of a station VRLA or Vented Lead-Acid (VLA) battery is required.

<b>Table 1-5</b> <b>Component Type - Control Circuitry Associated With Protective Functions</b> <b>Excluding distributed UFLS and distributed UVLS (see Table 3)</b> <b>Note: Table requirements apply to all Control Circuitry Components of Protection Systems, and SPSs except as noted.</b>		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Trip coils or actuators of circuit breakers, interrupting devices, or mitigating devices (regardless of any monitoring of the control circuitry).	6 calendar years	Verify that each trip coil is able to operate the circuit breaker, interrupting device, or mitigating device.
Electromechanical lockout devices which are directly in a trip path from the protective relay to the interrupting device trip coil (regardless of any monitoring of the control circuitry).	6 calendar years	Verify electrical operation of electromechanical lockout devices.
Unmonitored control circuitry associated with SPS.	12 calendar years	Verify all paths of the control circuits essential for proper operation of the SPS.
Unmonitored control circuitry associated with protective functions inclusive of all auxiliary relays.	12 calendar years	Verify all paths of the trip circuits inclusive of all auxiliary relays through the trip coil(s) of the circuit breakers or other interrupting devices.
Control circuitry associated with protective functions and/or SPS whose integrity is monitored and alarmed (See Table 2).	No periodic maintenance specified	None.

<b>Table 2 – Alarming Paths and Monitoring</b> In Tables 1-1 through 1-5 and Table 3, alarm attributes used to justify extended maximum maintenance intervals and/or reduced maintenance activities are subject to the following maintenance requirements		
<b>Component Attributes</b>	<b>Maximum Maintenance Interval</b>	<b>Maintenance Activities</b>
Any alarm path through which alarms in Tables 1-1 through 1-5 and Table 3 are conveyed from the alarm origin to the location where corrective action can be initiated, and not having all the attributes of the “Alarm Path with monitoring” category below.  Alarms are reported within 24 hours of detection to a location where corrective action can be initiated.	12 Calendar Years	Verify that the alarm path conveys alarm signals to a location where corrective action can be initiated.
Alarm Path with monitoring:  The location where corrective action is taken receives an alarm within 24 hours for failure of any portion of the alarming path from the alarm origin to the location where corrective action can be initiated.	No periodic maintenance specified	None.

Table 3 Maintenance Activities and Intervals for distributed UFLS and distributed UVLS Systems		
Component Attributes	Maximum Maintenance Interval	Maintenance Activities
Any unmonitored protective relay not having all the monitoring attributes of a category below.	6 calendar years	<p>Verify that settings are as specified</p> <p>For non-microprocessor relays:</p> <ul style="list-style-type: none"> <li>• Test and, if necessary calibrate</li> </ul> <p>For microprocessor relays:</p> <ul style="list-style-type: none"> <li>• Verify operation of the relay inputs and outputs that are essential to proper functioning of the Protection System.</li> <li>• Verify acceptable measurement of power system input values.</li> </ul>
<p>Monitored microprocessor protective relay with the following:</p> <ul style="list-style-type: none"> <li>• Internal self diagnosis and alarming (See Table 2).</li> <li>• Voltage and/or current waveform sampling three or more times per power cycle, and conversion of samples to numeric values for measurement calculations by microprocessor electronics.</li> </ul> <p>Alarming for power supply failure (See Table 2).</p>	12 calendar years	<p>Verify:</p> <ul style="list-style-type: none"> <li>• Settings are as specified.</li> <li>• Operation of the relay inputs and outputs that are essential to proper functioning of the Protection System.</li> <li>• Acceptable measurement of power system input values</li> </ul>
<p>Monitored microprocessor protective relay with preceding row attributes and the following:</p> <ul style="list-style-type: none"> <li>• Ac measurements are continuously verified by comparison to an independent ac measurement source, with alarming for excessive error (See Table 2).</li> <li>• Some or all binary or status inputs and control outputs are monitored by a process that continuously demonstrates ability to perform as designed, with alarming for failure (See Table 2).</li> </ul> <p>Alarming for change of settings (See Table 2).</p>	12 calendar years	<p>Verify only the unmonitored relay inputs and outputs that are essential to proper functioning of the Protection System.</p>



**Standard PRC-005-2 – Protection System Maintenance**

<b>Table 3                      Maintenance Activities and Intervals for distributed UFLS and distributed UVLS Systems</b>		
<b>Component Attributes</b>	<b>Maximum Maintenance Interval</b>	<b>Maintenance Activities</b>
Voltage and/or current sensing devices associated with UFLS or UVLS systems.	12 calendar years	Verify that current and/or voltage signal values are provided to the protective relays.
Protection System dc supply for tripping non-BES interrupting devices used only for a UFLS or UVLS system.	12 calendar years	Verify Protection System dc supply voltage.
Control circuitry between the UFLS or UVLS relays and electromechanical lockout and/or tripping auxiliary devices (excludes non-BES interrupting device trip coils).	12 calendar years	Verify the path from the relay to the lockout and/or tripping auxiliary relay (including essential supervisory logic).
Electromechanical lockout and/or tripping auxiliary devices associated only with UFLS or UVLS systems (excludes non-BES interrupting device trip coils).	12 calendar years	Verify electrical operation of electromechanical lockout and/or tripping auxiliary devices.
Control circuitry between the electromechanical lockout and/or tripping auxiliary devices and the non-BES interrupting devices in UFLS or UVLS systems, or between UFLS or UVLS relays (with no interposing electromechanical lockout or auxiliary device) and the non-BES interrupting devices (excludes non-BES interrupting device trip coils).	No periodic maintenance specified	None.
Trip coils of non-BES interrupting devices in UFLS or UVLS systems.	No periodic maintenance specified	None.

PRC-005 — Attachment A

**Criteria for a Performance-Based Protection System Maintenance Program**

**Purpose:** To establish a technical basis for initial and continued use of a performance-based Protection System Maintenance Program (PSMP).

**To establish the technical justification for the initial use of a performance-based PSMP:**

1. Develop a list with a description of Components included in each designated Segment of the Protection System Component population, with a minimum **Segment** population of 60 Components.
2. Maintain the Components in each Segment according to the time-based maximum allowable intervals established in Tables 1-1 through 1-5 and Table 3 until results of maintenance activities for the Segment are available for a minimum of 30 individual Components of the Segment.
3. Document the maintenance program activities and results for each Segment, including maintenance dates and Countable Events for each included Component.
4. Analyze the maintenance program activities and results for each Segment to determine the overall performance of the Segment and develop maintenance intervals.
5. Determine the maximum allowable maintenance interval for each Segment such that the Segment experiences **Countable Events** on no more than 4% of the Components within the Segment, for the greater of either the last 30 Components maintained or all Components maintained in the previous year.

**Segment** – *Protection Systems or components of a consistent design standard, or a particular model or type from a single manufacturer that typically share other common elements. Consistent performance is expected across the entire population of a Segment. A Segment must contain at least sixty (60) individual components.*

**Countable Event** – *A failure of a component requiring repair or replacement, any condition discovered during the maintenance activities in Tables 1-1 through 1-5 and Table 3 which requires corrective action, or a Misoperation attributed to hardware failure or calibration failure. Misoperations due to product design errors, software errors, relay settings different from specified settings, Protection System component configuration errors, or Protection System application errors are not included in Countable Events.*

**To maintain the technical justification for the ongoing use of a performance-based PSMP:**

1. At least annually, update the list of Protection System Components and Segments and/or description if any changes occur within the Segment.
2. Perform maintenance on the greater of 5% of the Components (addressed in the performance based PSMP) in each Segment or 3 individual Components within the Segment in each year.
3. For the prior year, analyze the maintenance program activities and results for each Segment to determine the overall performance of the Segment.

## **Standard PRC-005-2 – Protection System Maintenance**

---

4. Using the prior year's data, determine the maximum allowable maintenance interval for each Segment such that the Segment experiences Countable Events on no more than 4% of the Components within the Segment, for the greater of either the last 30 Components maintained or all Components maintained in the previous year.
5. If the Components in a Protection System Segment maintained through a performance-based PSMP experience 4% or more Countable Events, develop, document, and implement an action plan to reduce the Countable Events to less than 4% of the Segment population within 3 years.