

Standard EOP-003-2— Load Shedding Plans

Standard Development Roadmap

This section is maintained by the drafting team during the development of the standard and will be removed when the standard becomes effective.

Development Steps Completed:

1. Standards Committee approved the Supplemental SAR for posting on October 7, 2009 that expanded the SDT's scope to include EOP-003-1 but limiting that scope to only eliminating references to Under-frequency Load Shedding in EOP-003-1.
2. The Standards Drafting Team posted the standard for a third comment period June 11, 2010 – July 16, 2010.
3. The Standard Drafting Team conducted a pre-ballot review of the standard on June 11, 2010 – July 2, 2010
4. The Standard Drafting Team conducted an initial ballot of the standard and non-binding poll of the VRFs and VSLs on July 8, 2010 – July 17, 2010.
5. The Standard Drafting Team conducted a second ballot of the standard on July 24, 2010 – August 3, 2010.
6. The Standard Drafting Team conducted a successive ballot of the standard from September 24 – October 4, 2010.

Proposed Action Plan and Description of Current Draft:

This is the recirculation ballot period of the proposed standard.

Future Development Plan:

Anticipated Actions	Anticipated Date
1. Request BOT approval	November 3, 2010
2. File Standard with FERC	December, 2010

Standard EOP-003-2— Load Shedding Plans

A. Introduction

1. **Title:** Load Shedding Plans
2. **Number:** EOP-003-2
3. **Purpose:** A Balancing Authority and Transmission Operator operating with insufficient generation or transmission capacity must have the capability and authority to shed load rather than risk an uncontrolled failure of the Interconnection.
4. **Applicability:**
 - 4.1. Transmission Operators.
 - 4.2. Balancing Authorities.
5. **Effective Date:** One year following the first day of the first calendar quarter after applicable regulatory approvals (or the standard otherwise becomes effective the first day of the first calendar quarter after NERC Board of Trustees adoption in those jurisdictions where regulatory approval is not required).

B. Requirements

- R1.** After taking all other remedial steps, a Transmission Operator or Balancing Authority operating with insufficient generation or transmission capacity shall shed customer load rather than risk an uncontrolled failure of components or cascading outages of the Interconnection.
- R2.** Each Transmission Operator shall establish plans for automatic load shedding for undervoltage conditions if the Transmission Operator or its associated Transmission Planner(s) or Planning Coordinator(s) determine that an under-voltage load shedding scheme is required.
- R3.** Each Transmission Operator and Balancing Authority shall coordinate load shedding plans, excluding automatic under-frequency load shedding plans, among other interconnected Transmission Operators and Balancing Authorities.
- R4.** A Transmission Operator shall consider one or more of these factors in designing an automatic under voltage load shedding scheme: voltage level, rate of voltage decay, or power flow levels.
- R5.** A Transmission Operator or Balancing Authority shall implement load shedding, excluding automatic under-frequency load shedding, in steps established to minimize the risk of further uncontrolled separation, loss of generation, or system shutdown.
- R6.** After a Transmission Operator or Balancing Authority Area separates from the Interconnection, if there is insufficient generating capacity to restore system frequency following automatic underfrequency load shedding, the Transmission Operator or Balancing Authority shall shed additional load.
- R7.** The Transmission Operator shall coordinate automatic undervoltage load shedding throughout their areas with tripping of shunt capacitors, and other automatic actions that will occur under abnormal voltage, or power flow conditions
- R8.** Each Transmission Operator or Balancing Authority shall have plans for operator controlled manual load shedding to respond to real-time emergencies. The Transmission Operator or Balancing Authority shall be capable of implementing the load shedding in a timeframe adequate for responding to the emergency.

C. Measures

- M1.** Each Transmission Operator that has or directs the deployment of undervoltage load shedding facilities, shall have and provide upon request, its automatic load shedding plans.
(Requirement 2)
- M2.** Each Transmission Operator and Balancing Authority shall have and provide upon request its manual load shedding plans that will be used to confirm that it meets Requirement 8. (Part 1)

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

Regional Reliability Organizations shall be responsible for compliance monitoring.

1.2. Compliance Monitoring

One or more of the following methods will be used to assess compliance:

- Self-certification (Conducted annually with submission according to schedule.)
- Spot Check Audits (Conducted anytime with up to 30 days notice given to prepare.)
- Periodic Audit (Conducted once every three years according to schedule.)
- Triggered Investigations (Notification of an investigation must be made within 60 days of an event or complaint of noncompliance. The entity will have up to 30 days to prepare for the investigation. An entity may request an extension of the preparation period and the extension will be considered by the Compliance Monitor on a case-by-case basis.)

1.3. Additional Reporting Requirement

No additional reporting required.

1.4. Data Retention

Each Balancing Authority and Transmission Operator shall have its current, in-force load shedding plans.

If an entity is found non-compliant the entity shall keep information related to the noncompliance until found compliant or for two years plus the current year, whichever is longer.

Evidence used as part of a triggered investigation shall be retained by the entity being investigated for one year from the date that the investigation is closed, as determined by the Compliance Monitor.

The Compliance Monitor shall keep the last periodic audit report and all requested and submitted subsequent compliance records.

1.5. Additional Compliance Information

None

2. Violation Severity Levels

R#	Lower VSL	Moderate VSL	High VSL	Severe VSL
R1.	N/A	N/A	N/A	The Transmission Operator or Balancing Authority failed to shed customer load.
R2	N/A	N/A	N/A	The Transmission Operator did not establish plans for automatic load shedding for undervoltage conditions as directed by the requirement.
R3.	The responsible entity did not coordinate load shedding plans, as directed by the requirement, affecting 5% or less of its required entities.	The responsible entity did not coordinate load shedding plans, as directed by the requirement, affecting more than 5% up to (and including) 10% of its required entities.	The responsible entity did not coordinate load shedding plans, as directed by the requirement, affecting more than 10%, up to (and including) 15% or less, of its required entities.	The responsible entity did not coordinate load shedding plans, as directed by the requirement, affecting more than 15% of its required entities.
R4.	N/A	N/A	N/A	The Transmission Operator failed to consider at least one of the three elements voltage level, rate of voltage decay, or power flow levels) listed in the requirement.
R5.	N/A	N/A	N/A	The Transmission Operator or Balancing Authority failed to implement load shedding in steps established to minimize the risk of further uncontrolled separation, loss of generation, or system shutdown.

Standard EOP-003-2— Load Shedding Plans

R#	Lower VSL	Moderate VSL	High VSL	Severe VSL
R6.	N/A	N/A	N/A	The Transmission Operator or Balancing Authority failed to shed additional load after it had separated from the Interconnection when there was insufficient generating capacity to restore system frequency following automatic underfrequency load shedding.
R7.	The Transmission Operator did not coordinate automatic undervoltage load shedding with 5% or less of the types of automatic actions described in the Requirement.	The Transmission Operator did not coordinate automatic undervoltage load shedding with more than 5% up to (and including) 10% of the types of automatic actions described in the Requirement.	The Transmission Operator did not coordinate automatic undervoltage load shedding with more than 10% up to (and including) 15% of the types of automatic actions described in the Requirement.	The Transmission Operator did not coordinate automatic undervoltage load shedding with more than 15% of the types of automatic actions described in the Requirement.
R8.	N/A	The responsible entity did not have plans for operator controlled manual load shedding, as directed by the requirement.	The responsible entity has plans for manual load shedding but did not have the capability to implement the load shedding, as directed by the requirement.	The responsible entity did not have plans for operator controlled manual load shedding, as directed by the requirement nor had the capability to implement the load shedding, as directed by the requirement.

Standard EOP-003-2— Load Shedding Plans

E. Regional Differences

None identified.

Version History

Version	Date	Action	Change Tracking
0	April 1, 2005	Effective Date	New
0	August 8, 2005	Removed “Proposed” from Effective Date	Errata
1	November 1, 2006	Adopted by Board of Trustees	Revised
2	TBD	Modified R4, R5, R6 and associated VSLs for R2, R4, and R7 to clarify that the requirements don't apply to automatic underfrequency load shedding	Revised to eliminate redundancies with PRC-006-1