

May 6, 2014

**VIA ELECTRONIC FILING**

Rachelle Verret Morphy  
Saskatchewan Electric Reliability Authority  
2025 Victoria Avenue  
Regina, Saskatchewan, Canada S4P 0S1

Re: *North American Electric Reliability Corporation*

Dear Ms. Morphy:

The North American Electric Reliability Corporation (“NERC”) respectfully submits an update to the Phase 2 BES definition (“BES Definition”) in the *NERC Rules of Procedure*.

On November 21, 2013, the NERC Board of Trustees approved the BES Definition and authorized NERC management to make appropriate filings with the applicable governmental authorities. Today, NERC is submitting *Notice of Filing of Revisions to the BES Definition*. In this letter, NERC submits amendments to the *NERC Rules of Procedure* to include the new BES definition.

No additional changes to the BES Definition are proposed. NERC only updates the BES Definition in two appendices in the *NERC Rules of Procedure* as follows: pages 3-4 of Appendix 2, *Definitions Used in the Rules of Procedure*; and pages 4-6 of Appendix 5B, *Statement of Compliance Registry Criteria*. A copy of revised Appendix 2 and Appendix 5B is attached. These amendments to the *NERC Rules of Procedure* are necessary, appropriate, and in accordance with the Reliability Standard development process.

Respectfully submitted,

/s/ Willie L. Phillips

Willie L. Phillips  
Assistant General Counsel  
North American Electric Reliability Corporation  
1325 G Street NW, Suite 600  
Washington, D.C. 20005  
(202) 400-3000  
(202) 644-8099 – facsimile  
[Willie.Phillips@nerc.net](mailto:Willie.Phillips@nerc.net)

3353 Peachtree Road NE  
Suite 600, North Tower  
Atlanta, GA 30326  
404-446-2560 | [www.nerc.com](http://www.nerc.com)



## **NORTH AMERICAN ELECTRIC RELIABILITY CORPORATION**

### **DEFINITIONS USED IN THE RULES OF PROCEDURE**

#### **APPENDIX 2 TO THE RULES OF PROCEDURE**

**Effective: July 1, 2014  
(as noted below)**

New or revised definitions marked with # will become effective as defined terms on July 1, 2014 in accordance with the Bulk Electric System Order (Order No. 773) and the June 13, 2013 Order Granting Extension of Time.

## General

For purposes of the NERC Rules of Procedure, including all Appendices, the terms defined in this Appendix shall have the meanings set forth herein. For convenience of reference to the user, definitions of terms that are used in a particular Appendix may be repeated in that Appendix.

Where used in the Rules of Procedure, a defined term will be capitalized. Where a term defined in this Appendix appears in the Rules of Procedure but is not capitalized, the term is there being used in its ordinary and commonly understood meaning and not as defined in this Appendix (if different). Other terms that are not defined terms, such as the names of entities, organizations, committees, or programs; position titles; titles of documents or forms; section headings; geographic locations; and other terms commonly presented as proper nouns, may also be capitalized in the Rules of Procedure without being defined in this Appendix.

Definitions of terms in this Appendix that are marked with asterisks (\*\*) are taken from the NERC *Glossary of Terms Used in Reliability Standards*. Definitions of terms in this Appendix that are marked with “pluses” (++) are taken from Section 215 of the Federal Power Act or the Commission’s regulations at 18 C.F.R. Part 39 or Part 388.

Other terms used in the Rules of Procedure but not defined in this Appendix that have commonly understood and used technical meanings in the electric power industry, including applicable codes and standards, shall be construed in accordance with such commonly understood and used technical meanings.

## Specific Definitions

#“Acceptance of the Exception Request” or “Acceptance” means the determination that an eligible Exception Request (i.e., a Request permitted by section 4.1 of Appendix 5C) contains all the Required Information so that it can undergo substantive review.

“Adjacent Balancing Authority” means a Balancing Authority Area that is interconnected to another Balancing Authority Area either directly or via a multi-party agreement or transmission tariff.\*\*

“Adjusted Penalty Amount” means the proposed Penalty for a violation of a Reliability Standard as determined based on application of the adjustment factors identified in Section 4.3 of the *Sanction Guidelines* to the Base Penalty Amount.

“Advisories” or “Level 1 (Advisories)” is a notification issued by NERC in accordance with Section 810.3.1 of the Rules of Procedure.

“Alleged Violation” means a Possible Violation for which the Compliance Enforcement Authority has determined, based on an assessment of the facts and circumstances surrounding the Possible Violation, that evidence exists to indicate a Registered Entity has violated a Reliability Standard.

“Annual Audit Plan” means a plan developed annually by the Compliance Enforcement Authority that includes the Reliability Standards and Registered Entities to be audited and the schedule of Compliance Audits for the calendar year.

“Annual Report” means the annual report to be filed by NERC with FERC and other Applicable Governmental Authorities in accordance with Section 13.0 of Appendix 4D.

“Applicable Governmental Authority” means the FERC within the United States and the appropriate governmental authority with subject matter jurisdiction over reliability in Canada and Mexico.

“Applicable Requirement” means a Requirement of a CIP Standard that (i) expressly provides either (A) that compliance with the terms of the Requirement is required where or as technically feasible, or (B) that technical limitations may preclude compliance with the terms of the Requirement; or (ii) is subject to Appendix 4D by FERC directive.

#“Approval of the Exception Request” or “Approval” means the determination by NERC that an Exception Request meets the criteria to receive the requested Exception.

#“Balancing Authority” means the responsible entity that integrates resource plans ahead of time, maintains Load-interchange-generation balance within a Balancing Authority Area, and supports Interconnection frequency in real time.\*\*

#“Balancing Authority Area” means the collection of generation, transmission, and Loads within the metered boundaries of the Balancing Authority. The Balancing Authority maintains Load-resource balance within this area.\*\*

“Base Penalty Amount” means the proposed Penalty for a violation of a Reliability Standard as initially determined pursuant to Sections 4.1 and 4.2 of the NERC *Sanction Guidelines*, before application of any adjustment factors.

#“BES Definition” means the NERC definition of the Bulk Electric System as set forth in the NERC *Glossary of Terms Used in Reliability Standards*.

#“Blackstart Resource” means a generating unit(s) and its associated set of equipment which has the ability to be started without support from the System or is designed to remain energized without connection to the remainder of the System, with the ability to energize a bus, meeting the Transmission Operator’s restoration plan needs for Real and Reactive Power capability, frequency and voltage control, and that has been included in the Transmission Operator’s restoration plan.\*\*

“Board” or “Board of Trustees” means the Board of Trustees of NERC.

“Board of Trustees Compliance Committee,” “BOTCC” or “Compliance Committee” means the Compliance Committee of the NERC Board of Trustees.

#“Bulk Electric System” or “BES” means unless modified by the lists shown below, all Transmission Elements operated at 100 kV or higher and Real Power and Reactive Power resources connected at 100 kV or higher. This does not include facilities used in the local distribution of electric energy.

**Inclusions:**

- **I1** - Transformers with the primary terminal and at least one secondary terminal operated at 100 kV or higher unless excluded by application of Exclusion E1 or E3.
- **I2** - Generating resource(s) including the generator terminals through the high-side of the step-up transformer(s) connected at a voltage of 100 kV or above with:
  - a) Gross individual nameplate rating greater than 20 MVA. Or,
  - b) Gross plant/facility aggregate nameplate rating greater than 75 MVA.
- **I3** - Blackstart Resources identified in the Transmission Operator’s restoration plan.
- **I4** - Dispersed power producing resources that aggregate to a total capacity greater than 75 MVA (gross nameplate rating), and that are connected through a system designed primarily for delivering such capacity to a common point of connection at a voltage of 100 kV or above. Thus, the facilities designated as BES are:
  - a) The individual resources, and
  - b) The system designed primarily for delivering capacity from the point where those resources aggregate to greater than 75 MVA to a common point of connection at a voltage of 100 kV or above.
- **I5** - Static or dynamic devices (excluding generators) dedicated to supplying or absorbing Reactive Power that are connected at 100 kV or higher, or through a dedicated transformer with a high-side voltage of 100 kV or higher, or through a transformer that is designated in Inclusion I1 unless excluded by application of Exclusion E4.

**Exclusions:**

- **E1** - Radial systems: A group of contiguous transmission Elements that emanates from a single point of connection of 100 kV or higher and:
  - a) Only serves Load. Or,
  - b) Only includes generation resources, not identified in Inclusions I2, I3, or I4, with an aggregate capacity less than or equal to 75 MVA (gross nameplate rating). Or,
  - c) Where the radial system serves Load and includes generation resources, not identified in Inclusions I2, I3 or I4, with an aggregate capacity of non-retail generation less than or equal to 75 MVA (gross nameplate rating).

Note 1 – A normally open switching device between radial systems, as depicted on prints or one-line diagrams for example, does not affect this exclusion.

Note 2 – The presence of a contiguous loop, operated at a voltage level of 50 kV or less, between configurations being considered as radial systems, does not affect this exclusion.

- **E2** - A generating unit or multiple generating units on the customer's side of the retail meter that serve all or part of the retail Load with electric energy if: (i) the net capacity provided to the BES does not exceed 75 MVA, and (ii) standby, back-up, and maintenance power services are provided to the generating unit or multiple generating units or to the retail Load by a Balancing Authority, or provided pursuant to a binding obligation with a Generator Owner or Generator Operator, or under terms approved by the applicable regulatory authority.
- **E3** - Local networks (LN): A group of contiguous transmission Elements operated at less than 300 kV that distribute power to Load rather than transfer bulk power across the interconnected system. LN's emanate from multiple points of connection at 100 kV or higher to improve the level of service to retail customers and not to accommodate bulk power transfer across the interconnected system. The LN is characterized by all of the following:
  - a) Limits on connected generation: The LN and its underlying Elements do not include generation resources identified in Inclusions I2, I3, or I4 and do not have an aggregate capacity of non-retail generation greater than 75 MVA (gross nameplate rating);
  - b) Real Power flows only into the LN and the LN does not transfer energy originating outside the LN for delivery through the LN; and
  - c) Not part of a Flowgate or transfer path: The LN does not contain any part of a permanent Flowgate in the Eastern Interconnection, a major transfer path within the Western Interconnection, or a comparable monitored Facility in the ERCOT or Quebec Interconnections, and is not a monitored Facility included in an Interconnection Reliability Operating Limit (IROL).
- **E4** - Reactive Power devices installed for the sole benefit of a retail customer(s).

Note - Elements may be included or excluded on a case-by-case basis through the Rules of Procedure exception process.\*\*

“Bulk Power System” means, depending on the context: (i) Facilities and control systems necessary for operating an interconnected electric energy supply and transmission network (or any portion thereof), and electric energy from generating facilities needed to maintain

transmission system reliability. The term does not include facilities used in the local distribution of electric energy [++]. (ii) Solely for purposes of Appendix 4E, Bulk Electric System.

“Canadian” means one of the following: (a) a company or association incorporated or organized under the laws of Canada, or its designated representative(s) irrespective of nationality; (b) an agency of a federal, provincial, or local government in Canada, or its designated representative(s) irrespective of nationality; or (c) a self-representing individual who is a Canadian citizen residing in Canada.

#“Canadian Entity” means a Registered Entity (or, solely for purposes of Appendix 4D, a Responsible Entity) that is organized under Canadian federal or provincial law.

“Cascading” means the uncontrolled successive loss of System Elements triggered by an incident at any location. Cascading results in widespread electric service interruption that cannot be restrained from sequentially spreading beyond an area predetermined by studies.\*\*

“CCC” means the NERC Compliance and Certification Committee.

“Certification” means, depending on the context, (i) the process undertaken by NERC and a Regional Entity to verify that an entity is capable of responsibilities for tasks associated with a particular function such as a Balancing Authority, Transmission Operator and/or Reliability Coordinator; such Certification activities are further described in Section 500 and Appendix 5A of the NERC Rules of Procedure; or (ii) for purposes of Section 600 of the Rules of Procedure, an official recognition that indicates the recipient has passed a NERC exam or completed a specified number of Continuing Education Hours.

“Certification Staff” means individuals employed or contracted by NERC who have the authority to make initial determinations of Certification of entities performing reliability functions.

“Certification Team” means a team assembled by a Regional Entity that will be responsible for performing the activities included in the Certification process for an entity pursuant to Appendix 5A.

“Classified National Security Information” means Required Information that has been determined to be protected from unauthorized disclosure pursuant to Executive Order No. 12958, as amended, and/or the regulations of the NRC at 10 C.F.R. §95.35; or pursuant to any comparable provision of Canadian federal or provincial law.

“Clerk” means an individual assigned by the Compliance Enforcement Authority to perform administrative tasks relating to the conduct of hearings as described in Attachment 2, Hearing Procedures, to Appendix 4C.

“Commission” means the Federal Energy Regulatory Commission or FERC.

“Complaint” means an allegation that a Registered Entity violated a Reliability Standard.

“Compliance and Certification Manager” means individual/individuals within the Regional Entity that is/are responsible for monitoring compliance of entities with applicable NERC Reliability Standards.

“Compliance Audit” means a systematic, objective review and examination of records and activities to determine whether a Registered Entity meets the Requirements of applicable Reliability Standards.

“Compliance Audit Participants” means Registered Entities scheduled to be audited and the audit team members.

“Compliance Enforcement Authority” means NERC or the Regional Entity in their respective roles of monitoring and enforcing compliance with the NERC Reliability Standards.

“Compliance Enforcement Authority’s Area of Responsibility” means the Compliance Enforcement Authority’s Region. If a Regional Entity is the Compliance Enforcement Authority, the Compliance Enforcement Authority’s Area of Responsibility is shown in Exhibit A to the delegation agreement between the Regional Entity and NERC.

“Compliance Investigation” means a comprehensive investigation, which may include an on-site visit with interviews of the appropriate personnel, to determine if a violation of a Reliability Standard has occurred.

“Compliance Monitoring and Enforcement Program” or “CMEP” means, depending on the context (1) the NERC *Uniform Compliance Monitoring and Enforcement Program* (Appendix 4C to the NERC Rules of Procedure) or the Commission-approved program of a Regional Entity, as applicable, or (2) the program, department or organization within NERC or a Regional Entity that is responsible for performing compliance monitoring and enforcement activities with respect to Registered Entities’ compliance with Reliability Standards.

“Compliant Date” means the date by which a Responsible Entity is required to be in compliance with an Applicable Requirement of a CIP Standard.

“Confidential Business and Market Information” means any information that pertains to the interests of any entity, that was developed or acquired by that entity, and that is proprietary or competitively sensitive.

“Confidential Information” means (i) Confidential Business and Market Information; (ii) Critical Energy Infrastructure Information; (iii) personnel information that identifies or could be used to identify a specific individual, or reveals personnel, financial, medical, or other personal information; (iv) work papers, including any records produced for or created in the course of an evaluation or audit; (v) investigative files, including any records produced for or created in the course of an investigation; or (vi) Cyber Security Incident Information; provided, that public information developed or acquired by an entity shall be excluded from this definition; or (vii) for purposes of Appendix 4D, any other information that is designated as Confidential Information in Section 11.0 of Appendix 4D.

Appendix 2 to the NERC Rules of Procedure



“Confirmed Violation” means an Alleged Violation for which (1) the Registered Entity has accepted or not contested the Notice of Alleged Violation and Penalty or Sanction or other notification of the Alleged Violation, or (2) there has been the issuance of a final order from NERC or a Regional Entity Hearing Body finding a violation, Penalty or sanction, or (3) the period for requesting a hearing or an appeal has expired, or (4) the Registered Entity has executed a settlement agreement pursuant to Section 5.6.

“Continuing Education Hour” or “CE Hour” means based on sixty clock minutes, and includes at least fifty minutes of participation in a group or self-study learning activity that meets the criteria of the NERC Continuing Education Program.

“Continuing Education Program Provider” or “Provider” means the individual or organization offering a learning activity to participants and maintaining documentation required by Section 600 of the Rules of Procedure.

“Coordinated Functional Registration” means where two or more entities (parties) agree in writing upon a division of compliance responsibility among the parties for one or more Reliability Standard(s) applicable to a particular function, and/or for one or more Requirement(s)/sub-Requirement(s) within particular Reliability Standard(s).

“Covered Asset” means a Cyber Asset or Critical Cyber Asset that is subject to an Applicable Requirement.

“Credential” means a NERC designation that indicates the level of qualification achieved (i.e., reliability operator; balancing, interchange, and transmission operator; balancing and interchange operator; and transmission operator).

“Critical Assets” means Facilities, systems, and equipment which, if destroyed, degraded, or otherwise rendered unavailable, would affect the reliability or operability of the Bulk Electric System.\*\*

“Critical Cyber Assets” means Cyber Assets critical to the reliable operation of Critical Assets.\*\*

“Critical Energy Infrastructure Information” means specific engineering, vulnerability, or detailed design information about proposed or existing Critical Infrastructure that (i) relates details about the production, generation, transportation, transmission, or distribution of energy; (ii) could be useful to a person in planning an attack on Critical Infrastructure; and (iii) does not simply give the location of the Critical Infrastructure.++

“Critical Infrastructure” means existing and proposed systems and assets, whether physical or virtual, the incapacity or destruction of which would negatively affect security, economic security, public health or safety, or any combination of those matters.++

“Critical Infrastructure Protection Standard” or “CIP Standard” means any of NERC Reliability Standards CIP-002 through CIP-009.

“Cross-Border Regional Entity” means a Regional Entity that encompasses a part of the United States and a part of Canada or Mexico.++

“Cyber Assets” means programmable electronic devices and communication networks including hardware, software, and data.\*\*

“Cyber Security Incident” means any malicious or suspicious event that disrupts, or was an attempt to disrupt, the operation of those programmable electronic devices and communications networks including hardware, software and data that are essential to the Reliable Operation of the Bulk Power System.++

“Cyber Security Incident Information” means any information related to, describing, or which could be used to plan or cause a Cyber Security Incident.

“Days”, as used in Appendix 5A with respect to the Registration and Certification processes, means calendar days.

“Delegate” means a person to whom the Senior Manager of a Responsible Entity has delegated authority pursuant to Requirement R2.3 of CIP Standard CIP-003-1 (or any successor provision).

“Director of Compliance” means the Director of Compliance of NERC or of the Compliance Enforcement Authority, as applicable, or other individual designated by the Compliance Enforcement Authority who is responsible for the management and supervision of Compliance Staff, or his or her designee.

#“Disapproval of the Exception Request” or “Disapproval” means the determination by NERC that an Exception Request does not meet the criteria to receive the requested Exception.

#“Distribution Factor” means the portion of an Interchange Transaction, typically expressed in per unit that flows across a transmission facility (Flowgate).\*\*

“Distribution Provider” means the entity that provides and operates the “wires” between the transmission system and the end-use customer. For those end-use customers who are served at transmission voltages, the Transmission Owner also serves as the Distribution Provider. Thus, the Distribution Provider is not defined by a specific voltage, but rather as performing the distribution function at any voltage.\*\*

“Document” means, in addition to the commonly understood meaning of the term as information written or printed on paper, any electronically stored information, including writings, drawings, graphs, charts, photographs, sound recordings, images and other data or data compilations stored in any medium from which information can be obtained, and shall be translated by the producing party into reasonably usable form.

“Effective Date” means the date, as specified in a notice disapproving a TFE Request or terminating an approved TFE, on which the disapproval or termination becomes effective.

“Electric Reliability Organization” or “ERO” means the organization that is certified by the Commission under Section 39.3 of its regulations, the purpose of which is to establish and enforce Reliability Standards for the Bulk Power System in the United States, subject to Commission review. The organization may also have received recognition by Applicable Governmental Authorities in Canada and Mexico to establish and enforce Reliability Standards for the Bulk Power Systems of the respective countries.

“Element” means any electrical device with terminals that may be connected to other electrical devices such as a generator, transformer, circuit breaker, bus section, or transmission line. An Element may be comprised of one or more components.\*\*

“Eligible Reviewer” means a person who has the required security clearances or other qualifications, or who otherwise meets the applicable criteria, to have access to Confidential Information, Classified National Security Information, NRC Safeguards Information or Protected FOIA Information, as applicable to the particular information to be reviewed.

“End Date” means the last date of the period to be covered in a Compliance Audit.

“Essential Actions” or “Level 3 (Essential Actions)” is a notification issued by NERC in accordance with Section 810.3.3 of the Rules of Procedure.

“Evidentiary Hearing” means a hearing at which one or more Participants submits evidence for the record. A Testimonial Hearing is an Evidentiary Hearing, but an Evidentiary Hearing does not necessarily include the presentation of testimony by witnesses in person.

#“Exception” means either an Inclusion Exception or an Exclusion Exception.

#“Exception Procedure” means the procedure set forth in Appendix 5C.

“Exception Report” means information provided to the Compliance Enforcement Authority by a Registered Entity indicating that a violation of a Reliability Standard has occurred (e.g., a System Operating Limit has been exceeded) or enabling the Compliance Enforcement Authority to ascertain the Registered Entity’s compliance.

#“Exception Request” means a request made by a Submitting Entity in accordance with Appendix 5C for an Exception.

#“Exception Request Form” means the form adopted by each Regional Entity, in accordance with a template provided by NERC, for use by Submitting Entities in submitting Exception Requests; provided, that the Exception Request Form must include Section III.B as adopted by NERC.

“Exclusion Exception” means a determination that an Element that falls within the BES Definition should be excluded from the BES.

“Expiration Date” means the date on which an approved TFE expires.

“Facility” means a set of electrical equipment that operates as a single Bulk Electric System Element (e.g., a line, a generator, a shunt compensator, transformer, etc.)\*\*

“FERC” means the United States Federal Energy Regulatory Commission.

“Final Penalty Amount” means the final, proposed Penalty for violation of a Reliability Standard, determined in accordance with the *Sanction Guidelines*.

#“Flowgate” means 1.) A portion of the transmission system through which the Interchange Distribution Calculator calculates the power flow from Interchange Transactions. 2.) A mathematical construct, comprised of one or more monitored transmission Facilities and optionally one or more contingency Facilities, used to analyze the impact of power flows upon the Bulk Electric System.\*\*

“FOIA” means the U.S. Freedom of Information Act, 5 U.S.C. §552.

“Footprint” means the geographical or electric area served by an entity.

“Functional Entity” means an entity responsible for a function that is required to ensure the Reliable Operation of the electric grid as identified in the NERC Reliability Standards.

“Generator Operator” means the entity that operates generating unit(s) and performs the functions of supplying energy and Interconnected Operations Services.\*\*

“Generator Owner” means an entity that owns and maintains generating units.\*\*

“Hearing Body” or “Regional Entity Hearing Body” means the body established or designated by the Compliance Enforcement Authority to conduct hearings and issue decisions concerning disputed compliance matters in accordance with Attachment 2, Hearing Procedures, of Appendix 4C.

“Hearing Officer” means, depending on the context, (i) an individual employed or contracted by the Compliance Enforcement Authority and designated by the Compliance Enforcement Authority to preside over hearings conducted pursuant to Attachment 2, Hearing Procedures, of Appendix 4C, or (ii) solely for hearings conducted pursuant to Appendix 4E, (A) a CCC member or (B) an individual employed or contracted by NERC, as designated and approved by the CCC to preside over hearings conducted pursuant to the Hearing Procedures in Appendix E; the Hearing Officer shall not be a member of the Hearing Panel.

“Hearing Panel” means the five person hearing body established as set forth in the CCC Charter on a case by case basis and that is responsible for adjudicating a matter as set forth in Appendix 4E.

Appendix 2 to the NERC Rules of Procedure

“Hearing Procedures” means, depending on the context, (i) Attachment 2 to the NERC or a Regional Entity CMEP, as applicable, or (ii) the hearing procedures of the NERC Compliance and Certification Committee in Appendix 4E.

#“Inclusion Exception” means a determination that an Element that falls outside the BES Definition should be included in the BES.

“Interchange” means energy transfers that cross Balancing Authority boundaries.\*\*

“Interchange Authority” means the responsible entity that authorizes the implementation of valid and balanced Interchange Schedules between Balancing Authority Areas, and ensures communications of Interchange information for reliability assessment purposes.\*\*

#“Interchange Distribution Calculator” means the mechanism used by Reliability Coordinators in the Eastern Interconnection to calculate the distribution of Interchange Transactions over specific Flowgates. It includes a database of all Interchange Transactions and a matrix of the Distribution Factors for the Eastern Interconnection.\*\*

“Interchange Schedule” means an agreed-upon Interchange Transaction size (megawatts), start and end time, beginning and ending ramp times and rate, and type required for delivery and receipt of power and energy between the Source and Sink Balancing Authorities involved in the transaction.\*\*

“Interchange Transaction” means an agreement to transfer energy from a seller to a buyer that crosses one or more Balancing Authority Area boundaries.\*\*

“Interconnected Operations Service” means a service (exclusive of basic energy and Transmission Services) that is required to support the Reliable Operation of interconnected Bulk Electric Systems.\*\*

“Interconnection” means a geographic area in which the operation of Bulk Power System components is synchronized such that the failure of one or more of such components may adversely affect the ability of the operators of other components within the system to maintain Reliable Operation of the Facilities within their control.++

“Interconnection Reliability Operating Limit” means a System Operating Limit that, if violated, could lead to instability, uncontrolled separation, or Cascading outages that adversely impact the reliability of the Bulk Electric System.\*\*

“Interpretation” means an addendum to a Reliability Standard, developed in accordance with the NERC *Standard Processes Manual* and approved by the Applicable Governmental Authority(ies), that provides additional clarity about one or more Requirements in the Reliability Standard.

“ISO/RTO” means an independent transmission system operator or regional transmission organization approved by the FERC or the Public Utility Commission of Texas.

“Joint Registration Organization” means an entity that registers in the Compliance Registry to perform reliability functions for itself and on behalf of one or more of its members or related entities for which such members or related entities would otherwise be required to register.

#“Lead Entity” means the entity that submits Exception Request information that is common to a group of Submitting Entities that are submitting Exception Requests jointly.

“Lead Mediator” means a member of a mediation team formed pursuant to Appendix 4E who is selected by the members to coordinate the mediation process and serve as the mediation team’s primary contact with the Parties.

#“Load” means an end-user device or customer that receives power from the electric system.\*\*

“Load-Serving Entity” means an entity that secures energy and Transmission Service (and related Interconnected Operations Services) to serve the electrical demand and energy requirements of its end-use customers.\*\*

“Mapping” means the process of determining whether a Regional Entity’s Footprint is being served by Registered Entities.

“Material Change” means a change in facts that modifies Required Information in connection with an approved TFE. Examples of a Material Change could include, but are not limited to an increase in device count (but not a decrease), change in compensating measures, change in statement of basis for approval for the TFE, a change in the Expiration Date of the TFE, or a Responsible Entity achieving Strict Compliance with the Applicable Requirement.

“Material Change Report” means a report submitted by the Responsible Entity to the Regional Entity in the event there is a Material Change to the facts underlying an approved TFE pursuant to Section 4.0 of Appendix 4D.

“Mediation Settlement Agreement” means a written agreement entered into by the Parties to a mediation pursuant to Appendix 4E that resolves the dispute.

“Member” means a member of NERC pursuant to Article II of its Bylaws.

“Member Representatives Committee” or “MRC” means the body established pursuant to Article VIII of the NERC Bylaws.

#“Mexican Entity” means a Registered Entity that is organized under Mexican law.

“Mitigating Activities” means actions taken by a Registered Entity to correct and prevent recurrence of a noncompliance, whether or not the actions are embodied in a Mitigation Plan.

“Mitigation Plan” means an action plan developed by the Registered Entity to (1) correct a violation of a Reliability Standard and (2) prevent re-occurrence of the violation.

“NERC-Approved Learning Activity” means training that maintains or improves professional competence and has been approved by NERC for use in its Continuing Education Program.

“NERC Compliance Monitoring and Enforcement Program Implementation Plan” or “NERC Implementation Plan” means the annual NERC Compliance Monitoring and Enforcement Program Implementation Plan that specifies the Reliability Standards that are subject to reporting by Registered Entities to the Compliance Enforcement Authority in order to verify compliance and identifies the appropriate monitoring procedures and reporting schedules for each such Reliability Standard.

“NERC Compliance Registry,” “Compliance Registry” or “NCR” means a list, maintained by NERC pursuant to Section 500 of the NERC Rules of Procedure and Appendix 5B, the NERC *Statement of Compliance Registry Criteria*, of the owners, operators and users of the Bulk Power System, and the entities registered as their designees, that perform one or more functions in support of reliability of the Bulk Power System and are required to comply with one or more Requirements of Reliability Standards.

“NERC Identification Number” or “NERC ID” means a number given to NERC Registered Entities that will be used to identify the entity for certain NERC activities. Corporate entities may have multiple NERC IDs to show different corporate involvement in NERC activities.

“NERC Organization Certification” or “Organization Certification” means the process undertaken by NERC and a Regional Entity to verify that a new entity is capable of responsibilities for tasks associated with a particular function such as a Balancing Authority, Transmission Operator, and/or Reliability Coordinator; such certification activities are further described in Section 500 and Appendix 5A of the NERC Rules of Procedure.

“Net Energy for Load” or “NEL” means net generation of an electric system plus energy received from others less energy delivered to others through interchange. It includes system losses but excludes energy required for the storage of energy at energy storage facilities.

“Notice of Alleged Violation and Proposed Penalty or Sanction” means a notice issued by the Compliance Enforcement Authority to a Registered Entity pursuant to Section 5.3 of Appendix 4C.

“Notice of Completion of Enforcement Action” means a notice issued by the Compliance Enforcement Authority to a Registered Entity, pursuant to Section 5.10 of Appendix 4C, stating that an enforcement action is closed.

“Notice of Confirmed Violation” means a notice issued by the Compliance Enforcement Authority to a Registered Entity confirming the violation of one or more Reliability Standards.

“Notice of Penalty” means a notice prepared by NERC and filed with FERC, following approval by NERC of a Notice or other notification of Confirmed Violation or a settlement agreement, stating the Penalty or sanction imposed or agreed to for the Confirmed Violation or as part of the settlement.

“Notice of Possible Violation” means a notice issued by the Compliance Enforcement Authority to a Registered Entity that (1) states a Possible Violation has been identified, (2) provides a brief description of the Possible Violation, including the Reliability Standard Requirement(s) and the date(s) involved, and (3) instructs the Registered Entity to retain and preserve all data and records relating to the Possible Violation.

“NRC” means the United States Nuclear Regulatory Commission.

“NRC Safeguards Information” means Required Information that is subject to restrictions on disclosure pursuant to 42 U.S.C. §2167 and the regulations of the NRC at 10 C.F.R. §73.21-73.23; or pursuant to comparable provisions of Canadian federal or provincial law.

“Open Access Transmission Tariff” means an electronic transmission tariff accepted by the U.S. Federal Energy Regulatory Commission requiring the Transmission Service Provider to furnish to all shippers with non-discriminating service comparable to that provided by Transmission Owners to themselves.\*\*

#“Owner” means the owner(s) of an Element or Elements that is or may be determined to be part of the BES as a result of either the application of the BES Definition or an Exception, or another entity, such as an operator, authorized to act on behalf of the owner of the Element or Elements in the context of an Exception Request.

“Participant” means a Respondent and any other Person who is allowed or required by the Hearing Body or by FERC to participate as an intervenor in a proceeding conducted pursuant to the Hearing Procedures, and as used in the Hearing Procedures shall include, depending on the context, the members of the Compliance Staff that participate in a proceeding or the members of the Certification Staff that participate in a proceeding pursuant to Appendix 4E.

“Party” or “Parties” means a Person or the Persons participating in a mediation pursuant to Appendix 4E.

“Penalty” means and includes all penalties and sanctions, including but not limited to a monetary or non-monetary penalty; a limitation on an activity, function, operation or other appropriate sanction; or the addition of the Registered Entity or Respondent to a reliability watch list composed of major violators. Penalties must be within the range set forth in the NERC *Sanction Guidelines* approved by FERC pursuant to 18 C.F.R. Section 39.7(g)(2), and shall bear a reasonable relation to the seriousness of a Registered Entity’s or Respondent’s violation and take into consideration any timely efforts made by the Registered Entity or Respondent to remedy the violation.



“Periodic Data Submittals” means modeling, studies, analyses, documents, procedures, methodologies, operating data, process information or other information to demonstrate compliance with Reliability Standards and provided by Registered Entities to the Compliance Enforcement Authority on a time frame required by a Reliability Standard or an ad hoc basis.

“Person” means any individual, partnership, corporation, limited liability company, governmental body, association, joint stock company, public trust, organized group of persons, whether incorporated or not, or any other legal entity.

“Planning Authority” means the responsible entity that coordinates and integrates transmission Facilities and service plans, resource plans, and Protection Systems.\*\*

“Point of Delivery” means a location that a Transmission Service Provider specifies on its transmission system where an Interchange Transaction leaves or a Load-Serving Entity receives its energy.\*\*

“Point of Receipt” means a location that the Transmission Service Provider specifies on its transmission system where an Interchange Transaction enters or a generator delivers its output.

“Possible Violation” means the identification, by the Compliance Enforcement Authority, of a possible failure by a Registered Entity to comply with a Reliability Standard that is applicable to the Registered Entity.

“Preliminary Screen” means an initial evaluation of evidence indicating potential noncompliance with a Reliability Standard has occurred or is occurring, conducted by the Compliance Enforcement Authority for the purpose of determining whether a Possible Violation exists, and consisting of an evaluation of whether (1) the entity allegedly involved in the potential noncompliance is registered, (2) the Reliability Standard Requirement to which the evidence of potential noncompliance relates is applicable to a reliability function for which the entity is registered, and (3) if known, the potential noncompliance is not a duplicate of a Possible Violation or Alleged Violation which is currently being processed.

“Probation” means a step in the disciplinary process pursuant to Section 605 of the Rules of Procedure during which the certificate is still valid. During the probationary period, a subsequent offense of misconduct, as determined through the same process as described above, may be cause for more serious consequences.

“Protected FOIA Information” means Required Information, held by a governmental entity, that is subject to an exemption from disclosure under FOIA (5 U.S.C. §552(e)), under any similar state or local statutory provision, or under any comparable provision of Canadian federal or provincial law, which would be lost were the Required Information to be placed into the public domain.

“Protection System” means protective relays which respond to electrical quantities, communications systems necessary for correct operation of protective functions, voltage and current sensing devices providing inputs to protective relays, station dc supply associated with protective functions (including batteries, battery chargers, and non-battery-based dc supply), and

Appendix 2 to the NERC Rules of Procedure

control circuitry associated with protective functions through the trip coil(s) of the circuit breakers or other interrupting devices.\*\*

“Purchasing-Selling Entity” means the entity that purchases, or sells, and takes title to, energy, capacity, and Interconnected Operations Services. Purchasing-Selling Entities may be affiliated or unaffiliated merchants and may or may not own generating facilities.\*\*

#“Reactive Power” means the portion of electricity that establishes and sustains the electric and magnetic fields of alternating-current equipment. Reactive Power must be supplied to most types of magnetic equipment, such as motors and transformers. It also must supply the reactive losses on transmission facilities. Reactive Power is provided by generators, synchronous condensers, or electrostatic equipment such as capacitors and directly influences electric system voltage. It is usually expressed in kilovars (kvar) or megavars (Mvar).\*\*

#“Real Power” means the portion of electricity that supplies energy to the Load.\*\*

“Receiving Entity” means NERC or a Regional Entity receiving Confidential Information from an owner, operator, or user of the Bulk Power System or from any other party.

#“Recommendation” for purposes of Appendix 5C means the report to NERC containing the evaluation prepared in accordance with section 5.2 of Appendix 5C concerning whether or to what extent an Exception Request should be approved.

“Recommendations” or “Level 2 (Recommendations)” is a notification issued by NERC in accordance with Section 810.3.2 of the Rules of Procedure.

“Region” means the geographic area, as specified in a Regional Entity’s delegation agreement with NERC, within which the Regional Entity is responsible for performing delegated functions.

“Regional Criteria” means reliability requirements developed by a Regional Entity that are necessary to implement, to augment, or to comply with Reliability Standards, but which are not Reliability Standards. Such Regional Criteria may be necessary to account for physical differences in the Bulk Power System but are not inconsistent with Reliability Standards nor do they result in lesser reliability. Such Regional Criteria are not enforceable pursuant to NERC-delegated authorities, but may be enforced through other available mechanisms. Regional Criteria may include specific acceptable operating or planning parameters, guides, agreements, protocols or other documents.

“Regional Entity” means an entity having enforcement authority pursuant to 18 C.F.R. § 39.8.++

“Regional Entity Compliance Monitoring and Enforcement Program Implementation Plan” or “Regional Implementation Plan” means an annual plan, submitted by on or about October 1 of each year to NERC for approval that, in accordance with NERC Rule of Procedure Section 401.6 and the NERC Compliance Monitoring and Enforcement Program Implementation Plan, identifies (1) all Reliability Standards identified by NERC to be actively monitored during each year, (2) other Reliability Standards proposed for active monitoring by the Regional Entity, (3) Appendix 2 to the NERC Rules of Procedure

the methods to be used by the Regional Entity for reporting, monitoring, evaluation, and assessment of performance criteria with each Reliability Standard, and (4) the Regional Entity's Annual Audit Plan.

“Regional Reliability Standard” means a type of Reliability Standard that is applicable only within a particular Regional Entity or group of Regional Entities. A Regional Reliability Standard may augment, add detail to, or implement another Reliability Standard or cover matters not addressed by other Reliability Standards. Regional Reliability Standards, upon adoption by NERC and approval by the Applicable Governmental Authority(ies), shall be Reliability Standards and shall be enforced within the applicable Regional Entity or Regional Entities pursuant to delegated authorities or to procedures prescribed by the Applicable Governmental Authority.

“Registered Ballot Body” means that aggregation of all entities or individuals that qualify for one of the Segments approved by the Board of Trustees, and are registered with NERC as potential ballot participants in the voting on proposed Reliability Standards.

“Registered Entity” means an owner, operator, or user of the Bulk Power System, or the entity registered as its designee for the purpose of compliance, that is included in the NERC Compliance Registry.

“Registration” or “Organization Registration” means the processes undertaken by NERC and Regional Entities to identify which entities are responsible for reliability functions within the Regional Entity's Region.

#“Rejection of the Exception Request” or “Rejection” means the determination that an Exception Request is not an eligible Exception Request (i.e., a Request permitted by section 4.1 of Appendix 5C) or does not contain all the Required Information in accordance with section 4.5 of Appendix 5C in order to be reviewed for substance.

“Reliability Coordinator” means the entity that is the highest level of authority who is responsible for the Reliable Operation of the Bulk Electric System, has the Wide Area view of the Bulk Electric System, and has the operating tools, processes and procedures, including the authority to prevent or mitigate emergency operating situations in both next-day analysis and real-time operations. The Reliability Coordinator has the purview that is broad enough to enable the calculation of Interconnection Reliability Operating Limits, which may be based on the operating parameters of transmission systems beyond any Transmission Operator's vision.\*\*

“Reliability Coordinator Area” means the collection of generation, transmission and loads within the boundaries of the Reliability Coordinator. Its boundary coincides with one or more Balancing Authority Areas.\*\*

“Reliability Standard” means a requirement to provide for Reliable Operation of the Bulk Power System, including without limiting the foregoing, requirements for the operation of existing Bulk Power System Facilities, including cyber security protection, and including the design of planned additions or modifications to such Facilities to the extent necessary for Reliable Operation of the Appendix 2 to the NERC Rules of Procedure

Bulk Power System, but the term does not include any requirement to enlarge Bulk Power System Facilities or to construct new transmission capacity or generation capacity. A Reliability Standard shall not be effective in the United States until approved by the Federal Energy Regulatory Commission and shall not be effective in other jurisdictions until made or allowed to become effective by the Applicable Governmental Authority.

“Reliability Standards Development Plan” means the forward-looking plan developed by NERC on an annual basis setting forth the Reliability Standards development projects that are scheduled to be worked on during the ensuing three-year period, as specified in Section 310 of the Rules of Procedure.

“Reliable Operation” means operating the Elements of the Bulk Power System within equipment and electric system thermal, voltage, and stability limits so that instability, uncontrolled separation, or Cascading failures of such system will not occur as a result of a sudden disturbance, including a Cyber Security Incident, or unanticipated failure of system Elements.++

“Remedial Action Directive” means an action (other than a Penalty or sanction) required by a Compliance Enforcement Authority that (1) is to bring a Registered Entity into compliance with a Reliability Standard or to avoid a Reliability Standard violation, and (2) is immediately necessary to protect the reliability of the Bulk Power System from an imminent or actual threat.

“Reporting Entity” means an entity required to provide data or information requested by NERC or a Regional Entity in a request for data or information pursuant to Section 1600 of the Rules of Procedure.

“Requirement” means an explicit statement in a Reliability Standard that identifies the functional entity responsible, the action or outcome that must be achieved, any conditions achieving the action or outcome, and the reliability-related benefit of the action or outcome. Each Requirement shall be a statement with which compliance is mandatory.

“Required Date” means the date given a Registered Entity in a notice from the Compliance Enforcement Authority by which some action by the Registered Entity is required.

#“Required Information” means, as applicable, either (i) the information required to be provided in a TFE Request, as specified in Section 4.0 of Appendix 4D; or (ii) the information required to be provided in an Exception Request, as specified in section 4.0 of Appendix 5C.

“Reserve Sharing Group” means a group whose members consist of two or more Balancing Authorities that collectively maintain, allocate, and supply operating reserves required for each Balancing Authority’s use in recovering from contingencies within the group. Scheduling energy from an Adjacent Balancing Authority to aid recovery need not constitute reserve sharing provided the transaction is ramped in over a period the supplying party could reasonably be expected to load generation in (e.g. ten minutes). If the transaction is ramped in quicker, (e.g., between zero and ten minutes), then, for the purposes of disturbance control performance, the areas become a Reserve Sharing Group.\*\*

“Resource Planner” means the entity that develops a long-term (generally one year and beyond) plan for the resource adequacy of specific loads (customer demand and energy requirements) within a Planning Authority area.\*\*

“Respondent” means, depending on the context, the Registered Entity, who is the subject of the Notice of Alleged Violation, contested Mitigation Plan or contested Remedial Action Directive that is the basis for the proceeding, whichever is applicable, or the Registered Entity that is the subject of the Certification decision that is the basis for a proceeding under Appendix 4E.

“Responsible Entity” means an entity that is registered for a reliability function in the NERC Compliance Registry and is responsible for complying with an Applicable Requirement, as specified in the “Applicability” section of the CIP Standard.

“Revoked” means a NERC certificate that has been suspended for more than twelve months. While in this state, a certificate holder can not perform any task that requires an operator to be NERC-certified. The certificate holder will be required to pass an exam to be certified again. Any CE Hours accumulated prior to or during the revocation period will not be counted towards Credential Maintenance.

“Revoke for Cause” means a step in the disciplinary process pursuant to Section 605 of the Rules of Procedure during which the certificate is no longer valid and requiring successfully passing an exam to become certified. However, an exam will not be authorized until the revocation period expires. CE Hours earned before or during this revocation period will not be counted for maintaining a Credential.

#“Scope of Responsibility” means the registered functions of a Planning Authority, Reliability Coordinator, Transmission Operator, Transmission Planner or Balancing Authority and the geographical or electric region in which the Planning Authority, Reliability Coordinator, Transmission Operator, Transmission Planner or Balancing Authority operates to perform its registered functions, or with respect to a Regional Entity, its Regional Entity Region.

#“Section I Required Information” means Required Information that is to be provided in Section I of a Submitting Entity’s Exception Request.

#“Section II Required Information” means Required Information that is to be provided in Section II of a Submitting Entity’s Exception Request.

#“Section III Required Information” means Required Information that is to be provided in Section III of a Submitting Entity’s Exception Request.

“Sector” means a group of Members of NERC that are Bulk Power System owners, operators, or users or other persons and entities with substantially similar interests, including governmental entities, as pertinent to the purposes and operations of NERC and the operation of the Bulk Power System, as defined in Article II, Section 4 of the NERC Bylaws. Each Sector shall constitute a class of Members for purposes of the New Jersey Nonprofit Corporation Act.

“Segment” means one of the subsets of the Registered Ballot Body whose members meet the qualification criteria for the subset.

“Self-Certification” means an attestation by a Registered Entity that it is compliant or non-compliant with a Reliability Standard Requirement that is the subject of the Self-Certification, or that it does not own Facilities that are subject to the Reliability Standard Requirement, or that the Reliability Standard Requirement is not applicable to the Registered Entity.

“Self-Report” means a report by a Registered Entity stating that the Registered Entity believes it has, or may have, violated a Reliability Standard.

“Senior Manager” means the person assigned by the Responsible Entity, in accordance with CIP Standard CIP-003-1 Requirement R2 (or subsequent versions), to have overall responsibility for leading and managing the Responsible Entity’s implementation of, and adherence to, the CIP Standards.

#“Sink Balancing Authority” means the Balancing Authority in which the Load (sink) is located for an Interchange Transaction.\*\*

“Source Balancing Authority” means the Balancing Authority in which the generation (source) is located for an Interchange Transaction.\*\*

#“Special Protection System” means an automatic protection system designed to detect abnormal or predetermined system conditions, and take corrective actions other than and/or in addition to the isolation of faulted components to maintain system reliability. Such action may include changes in demand, generation (MW and Mvar), or system configuration to maintain system stability, acceptable voltage, or power flows. A Special Protection System does not include (a) underfrequency or undervoltage Load shedding or (b) fault conditions that must be isolated, or (c) out-of-step relaying (not designed as an integral part of a Special Protection System).\*\*

“Spot Check” means a process in which the Compliance Enforcement Authority requests a Registered Entity to provide information (1) to support the Registered Entity’s Self-Certification, Self-Report, or Periodic Data Submittal and to assess whether the Registered Entity complies with Reliability Standards, or (2) as a random check, or (3) in response to operating problems or system events.

“Staff” or “Compliance Staff” means individuals employed or contracted by NERC or the Compliance Enforcement Authority who have the authority to make initial determinations of compliance or violation with Reliability Standards by Registered Entities and associated Penalties and Mitigation Plans.

“Strict Compliance” means compliance with the terms of an Applicable Requirement without reliance on a Technical Feasibility Exception.

#“Submitting Entity” means (i) an owner, operator, or user of the Bulk Power System or any other party that submits information to NERC or a Regional Entity that it reasonably believes

contains Confidential Information or, (ii) solely for purposes of Appendix 5C, the entity that submits an Exception Request in accordance with section 4.0 of Appendix 5C.

“Suspended” means certificate status due to an insufficient number of CE Hours being submitted prior to the expiration of a certificate. While in this state, a certificate holder can not perform any task that requires an operator to be NERC-certified.

“System” means a combination of generation, transmission and distribution components.\*\*

“System Operating Limit” means the value (such as MW, Mvar, amperes, frequency or volts) that satisfies the most limiting of the prescribed operating criteria for a specified system configuration to ensure operation within acceptable reliability criteria.\*\*

“Technical Advisor” means any Staff member, third-party contractor, or industry stakeholder who satisfies NERC’s or the Compliance Enforcement Authority’s (as applicable) conflict of interest policy and is selected to assist in a proceeding by providing technical advice to the Hearing Officer and/or the Hearing Body or Hearing Panel.

“Technical Feasibility Exception” or “TFE” means an exception from Strict Compliance with the terms of an Applicable Requirement on grounds of technical feasibility or technical limitations in accordance with one or more of the criteria in section 3.0 of Appendix 4D.

#“Technical Review Panel” means a panel established pursuant to section 5.3 of Appendix 5C.

“Termination of Credential” means a step in the disciplinary process pursuant to Section 605 of the Rules of Procedure whereby a Credential is permanently Revoked.

“Testimonial Hearing” means an Evidentiary Hearing at which the witness or witnesses on behalf of one or more Participants appears in person to present testimony and be subject to cross-examination.

“TFE Request” means a request submitted by a Responsible Entity in accordance with Appendix 4D for an exception from Strict Compliance with an Applicable Requirement.

“Transmission Customer” means 1. any eligible customer (or its designated agent) that can or does execute a Transmission Service agreement or can and does receive Transmission Service. 2. Any of the following responsible entities: Generator Owner, Load-Serving Entity, or Purchasing-Selling Entity.\*\*

“Transmission Operator” means the entity responsible for the reliability of its “local” transmission system, and that operates or directs the operations of the transmission Facilities.\*\*

“Transmission Owner” means the entity that owns and maintains transmission Facilities.\*\*

“Transmission Planner” means the entity that develops a long-term (generally one year and beyond) plan for the reliability (adequacy) of the interconnected bulk electric transmission systems within its portion of the Planning Authority area.\*\*

“Transmission Service” means services provided to the Transmission Customer by the Transmission Service Provider to move energy from a Point of Receipt to a Point of Delivery.\*\*

“Transmission Service Provider” means the entity that administers the transmission tariff and provides Transmission Service to Transmission Customers under applicable Transmission Service agreements.\*\*

“Variance” means an aspect or element of a Reliability Standard that applies only within a particular Regional Entity or group of Regional Entities, or to a particular entity or class of entities. A Variance allows an alternative approach to meeting the same reliability objective as the Reliability Standard, and is typically necessitated by a physical difference. A Variance is embodied within a Reliability Standard and as such, if adopted by NERC and approved by the Applicable Governmental Authority(ies), shall be enforced within the applicable Regional Entity or Regional Entities pursuant to delegated authorities or to procedures prescribed by the Applicable Governmental Authority.

“Violation Risk Factor” or “VRF” means a factor (lower, medium or high) assigned to each Requirement of a Reliability Standard to identify the potential reliability significance of noncompliance with the Requirement.

“Violation Severity Level” or “VSL” means a measure (lower, moderate, high or severe) of the degree to which compliance with a Requirement was not achieved.

“Wide Area” means the entire Reliability Coordinator Area as well as the critical flow and status information from adjacent Reliability Coordinator Areas as determined by detailed system studies to allow the calculation of Interconnected Reliability Operating Limits.\*\*



## **Appendix 5B**

# **Statement of Compliance Registry Criteria**

### **Revision 5.1**

**Effective: July 1, 2014**

**(as noted below)**

The highlighted terms “Bulk Electric System” and “Load” in this document will become effective as defined terms on July 1, 2014 in accordance with the Bulk Electric System Order (Order No. 773) and the June 13, 2013 Order Granting Extension of Time. See Appendix 2 of the Rules of Procedure.

# Statement of Compliance Registry Criteria (Revision 5.1)

## Summary

Since becoming the Electric Reliability Organization (ERO), NERC has initiated a program to identify candidate organizations for its Compliance Registry. The program, conducted by NERC and the Regional Entities<sup>1</sup>, will also confirm the functions and information now on file for currently-registered organizations. NERC and the Regional Entities have the obligation to identify and register all entities that meet the criteria for inclusion in the Compliance Registry, as further explained in the balance of this document.

This document describes how NERC will identify organizations that may be candidates for Registration and assign them to the Compliance Registry.

Organizations will be responsible to register and to comply with approved Reliability Standards to the extent that they are owners, operators, and users of the Bulk Power System, perform a function listed in the functional types identified in Section II of this document, and are material to the Reliable Operation of the interconnected Bulk Power System as defined by the criteria and notes set forth in this document. NERC will apply the following principles to the Compliance Registry:

- In order to carry out its responsibilities related to enforcement of Reliability Standards, NERC must identify the owners, operators, and users of the Bulk Power System who have a material impact<sup>2</sup> on the Bulk Power System through a Compliance Registry. NERC and the Regional Entities will make their best efforts to identify all owners, users and operators who have a material reliability impact on the Bulk Power System in order to develop a complete and current Compliance Registry list. The Compliance Registry will be updated as required and maintained on an on-going basis.
- Organizations listed in the Compliance Registry are responsible and will be monitored for compliance with applicable mandatory Reliability Standards. They will be subject to NERC's and the Regional Entities' Compliance Monitoring and Enforcement Programs.

---

<sup>1</sup> The term “Regional Entities” includes Cross-Border Regional Entities.

<sup>2</sup> The criteria for determining whether an entity will be placed on the Compliance Registry are set forth in the balance of this document. At any time a person may recommend in writing, with supporting reasons, to the Director of Compliance that an organization be added to or removed from the Compliance Registry, pursuant to NERC ROP 501.1.3.5.

- NERC and Regional Entities will not monitor nor hold those not in the Compliance Registry responsible for compliance with the Reliability Standards. An entity which is not initially placed on the Compliance Registry, but which is identified subsequently as having a material reliability impact, will be added to the Compliance Registry. Such entity will not be subject to a sanction or Penalty by NERC or the Regional Entity for actions or inactions prior to being placed on the Compliance Registry, but may be required to comply with a Remedial Action Directive or Mitigation Plan in order to become compliant with applicable Reliability Standards. After such entity has been placed on the Compliance Registry, it shall be responsible for complying with Reliability Standards and may be subject to sanctions or Penalties as well as any Remedial Action Directives and Mitigation Plans required by the Regional Entities or NERC for future violations, including any failure to follow a Remedial Action Directive or Mitigation Plan to become compliant with Reliability Standards.
- Required compliance by a given organization with the Reliability Standards will begin the later of (i) inclusion of that organization in the Compliance Registry and (ii) approval by the Applicable Governmental Authority of mandatory Reliability Standards applicable to the Registered Entity.

Entities responsible for funding NERC and the Regional Entities have been identified in the budget documents filed with FERC. Presence on or absence from the Compliance Registry has no bearing on an entity's independent responsibility for funding NERC and the Regional Entities.

## **Background**

In 2005, NERC and the Regional Entities conducted a voluntary organization registration program limited to Balancing Authorities, Planning Authorities, regional reliability organizations, Reliability Coordinators, Transmission Operators, and Transmission Planners. The list of the entities that were registered constitutes what NERC considered at that time as its Compliance Registry.

NERC has recently initiated a broader program to identify additional organizations potentially eligible to be included in the Compliance Registry and to confirm the information of organizations currently on file. NERC believes this is a prudent activity at this time because:

- As of July 20, 2006, NERC was certified as the ERO created for the U.S. by the Energy Policy Act of 2005 (EPAct) and FERC Order 672. NERC has also filed with Canadian authorities for similar recognition in their respective jurisdictions.
- FERC's Order 672 directs that owners, operators and users of the Bulk Power System shall be registered with the ERO and the appropriate Regional Entities.
- As the ERO, NERC has filed its current Reliability Standards with FERC and with Canadian authorities. As accepted and approved by FERC and appropriate Canadian authorities, the Reliability Standards are no longer voluntary, and organizations that do not fully comply with them may face Penalties or other sanctions determined and levied by NERC or the Regional Entities.

- NERC’s Reliability Standards include compliance Requirements for additional reliability function types beyond the six types registered by earlier registration programs.
- Based on selection as the ERO, the extension and expansion of NERC’s current Registration program<sup>3</sup> is the means by which NERC and the Regional Entities will plan, manage and execute Reliability Standard compliance oversight of owners, operators, and users of the Bulk Power System.
- Organizations listed in the Compliance Registry are subject to NERC’s and the Regional Entities’ Compliance Monitoring and Enforcement Programs.

## Statement of Issue

As the ERO, NERC intends to comprehensively and thoroughly protect the reliability of the grid. To support this goal NERC will include in its Compliance Registry each entity that NERC concludes can materially impact the reliability of the Bulk Power System. However, the potential costs and effort of ensuring that every organization potentially within the scope of “owner, operator, and user of the Bulk Power System” becomes registered while ignoring their impact upon reliability, would be disproportionate to the improvement in reliability that would reasonably be anticipated from doing so.

NERC wishes to identify as many organizations as possible that may need to be listed in its Compliance Registry. Identifying these organizations is necessary and prudent at this time for the purpose of determining resource needs, both at the NERC and Regional Entity level, and to begin the process of communication with these entities regarding their potential responsibilities and obligations. NERC and the Regional Entities believe that primary candidate entities can be identified at this time, while other entities can be identified later, as and when needed. Selection principles and criteria for the identification of these initial entities are required. This list will become the “Initial Non-binding Organization Registration List”. With FERC having made the approved Reliability Standards enforceable, this list becomes the NERC Compliance Registry.

## Resolution

NERC and the Regional Entities have identified two principles they believe are key to the entity selection process. These are:

1. There needs to be consistency between Regions and across the continent with respect to which entities are registered, and;
2. Any entity reasonably deemed material to the reliability of the Bulk Bower System will be registered, irrespective of other considerations.

To address the second principle the Regional Entities, working with NERC, will identify and register any entity they deem material to the reliability of the Bulk Power System.

In order to promote consistency, NERC and the Regional Entities intend to use the following criteria as the basis for determining whether particular entities should be identified as candidates

---

<sup>3</sup> See: NERC ERO Application; Exhibit C; Section 500 – Organization Registration and Certification.

for Registration. All organizations meeting or exceeding the criteria will be identified as candidates.

The following four groups of criteria (Sections I-IV) plus the statements in Section V will provide guidance regarding an entity's Registration status:

- Section I determines if the entity is an owner, operator, or user of the Bulk Power System and, hence, a candidate for organization Registration.
- Section II uses NERC's current functional type definitions to provide an initial determination of the functional types for which the entities identified in Section I should be considered for Registration.
- Section III lists the criteria regarding smaller entities; these criteria can be used to forego the Registration of entities that were selected to be considered for Registration pursuant to Sections I and II and, if circumstances change, for later removing entities from the Registration list that no longer meet the relevant criteria.
- Section IV — additional criteria for joint Registration. Joint Registration criteria may be used by joint action agencies, generation and transmission cooperatives and other entities which agree upon a clear division of compliance responsibility for Reliability Standards by written agreement. Pursuant to FERC's directive in paragraph 107 of Order No. 693, rules pertaining to joint Registration and Joint Registration Organizations will now be found in Sections 501 and 507 of the NERC Rules of Procedure.

I. Entities that use, own or operate Elements of the Bulk Electric System as established by NERC's approved definition of Bulk Electric System below are (i) owners, operators, and users of the Bulk Power System and (ii) candidates for Registration:

*"Bulk Electric System" or "BES" means unless modified by the lists shown below, all Transmission Elements operated at 100 kV or higher and Real Power and Reactive Power resources connected at 100 kV or higher. This does not include facilities used in the local distribution of electric energy.*

***Inclusions:***

- *11 - Transformers with the primary terminal and at least one secondary terminal operated at 100 kV or higher unless excluded by application of Exclusion E1 or E3.*
- *12 - Generating resource(s) including the generator terminals through the high-side of the step-up transformer(s) connected at a voltage of 100 kV or above with:
  - d) *Gross individual nameplate rating greater than 20 MVA. Or,*
  - e) *Gross plant/facility aggregate nameplate rating greater than 75 MVA.**
- *13 - Blackstart Resources identified in the Transmission Operator's restoration plan.*
- *14 - Dispersed power producing resources that aggregate to a total capacity greater than 75 MVA (gross nameplate rating), and that are connected through a system designed primarily for delivering such capacity to a common point of connection at a voltage of 100 kV or above. Thus, the facilities designated as BES are:
  - a) *The individual resources, and**

b) The system designed primarily for delivering capacity from the point where those resources aggregate to a greater than 75 MVA to a common point of connection at a voltage of 100 kV or above.

- **I5** - Static or dynamic devices (excluding generators) dedicated to supplying or absorbing Reactive Power that are connected at 100 kV or higher, or through a dedicated transformer with a high-side voltage of 100 kV or higher, or through a transformer that is designated in Inclusion II unless excluded by application of Exclusion E4.

**Exclusions:**

- **E1** - Radial systems: A group of contiguous transmission Elements that emanates from a single point of connection of 100 kV or higher and:
  - a) Only serves Load. Or,
  - b) Only includes generation resources, not identified in Inclusions I2, I3, or I4, with an aggregate capacity less than or equal to 75 MVA (gross nameplate rating). Or,
  - c) Where the radial system serves Load and includes generation resources, not identified in Inclusions I2, I3 or I4, with an aggregate capacity of non-retail generation less than or equal to 75 MVA (gross nameplate rating).

Note 1 – A normally open switching device between radial systems, as depicted on prints or one-line diagrams for example, does not affect this exclusion.

Note 2 – The presence of a contiguous loop operated at a voltage level of 50 kV or less, between configurations being considered as radial systems, does not affect this exclusion.

- **E2** - A generating unit or multiple generating units on the customer's side of the retail meter that serve all or part of the retail Load with electric energy if: (i) the net capacity provided to the BES does not exceed 75 MVA, and (ii) standby, back-up, and maintenance power services are provided to the generating unit or multiple generating units or to the retail Load by a Balancing Authority, or provided pursuant to a binding obligation with a Generator Owner or Generator Operator, or under terms approved by the applicable regulatory authority.
- **E3** - Local networks (LN): A group of contiguous transmission Elements operated at less than 300 kV that distribute power to Load rather than transfer bulk power across the interconnected system. LN's emanate from multiple points of connection at 100 kV or higher to improve the level of service to retail customers and not to accommodate bulk power transfer across the interconnected system. The LN is characterized by all of the following:
  - a) Limits on connected generation: The LN and its underlying Elements do not include generation resources identified in Inclusions I2, I3, or I4 and do not have an aggregate capacity of non-retail generation greater than 75 MVA (gross nameplate rating);
  - b) Real Power flows only into the LN and the LN does not transfer energy originating outside the LN for delivery through the LN; and
  - c) Not part of a Flowgate or transfer path: The LN does not contain any part of a permanent Flowgate in the Eastern Interconnection, a major transfer path within

*the Western Interconnection, or a comparable monitored Facility in the ERCOT or Quebec Interconnections, and is not a monitored Facility included in an Interconnection Reliability Operating Limit (IROL).*

- *E4 - Reactive Power devices installed for the sole benefit of a retail customer(s).*

*Note - Elements may be included or excluded on a case-by-case basis through the Rules of Procedure exception process.*

II. Entities identified in Part I above will be categorized as Registration candidates who may be subject to Registration under one or more appropriate Functional Entity types based on a comparison of the functions the entity normally performs against the following function type definitions:

<b>Function Type</b>	<b>Acronym</b>	<b>Definition/Discussion</b>
Balancing Authority	BA	The responsible entity that integrates resource plans ahead of time, maintains <b>Load</b> -interchange-generation balance within a Balancing Authority Area, and supports Interconnection frequency in real-time.
Distribution Provider	DP	Provides and operates the “wires” between the transmission system and the end-use customer. For those end-use customers who are served at transmission voltages, the Transmission Owner also serves as the Distribution Provider. Thus, the Distribution Provider is not defined by a specific voltage, but rather as performing the distribution function at any voltage.
Generator Operator	GOP	The entity that operates generating unit(s) and performs the functions of supplying energy and Interconnected Operations Services.
Generator Owner	GO	Entity that owns and maintains generating units.
Interchange Authority	IA	The responsible entity that authorizes implementation of valid and balanced Interchange Schedules between Balancing Authority Areas, and ensures communication of Interchange information for reliability assessment purposes.
Load-Serving Entity	LSE	Secures energy and Transmission Service (and related Interconnected Operations Services) to serve the electrical demand and energy requirements of its end-use customers.

<b>Function Type</b>	<b>Acronym</b>	<b>Definition/Discussion</b>
Planning Authority	PA	The responsible entity that coordinates and integrates transmission Facilities and service plans, resource plans, and Protection Systems.
Purchasing-Selling Entity	PSE	The entity that purchases, or sells, and takes title to, energy, capacity, and Interconnected Operations Services. PSE may be affiliated or unaffiliated merchants and may or may not own generating Facilities.
Reliability Coordinator	RC	The entity that is the highest level of authority who is responsible for the Reliable Operation of the Bulk Electric System, has the Wide Area view of the Bulk Electric System, and has the operating tools, processes and procedures, including the authority to prevent or mitigate emergency operating situations in both next-day analysis and real-time operations. The Reliability Coordinator has the purview that is broad enough to enable the calculation of Interconnection Reliability Operating Limits, which may be based on the operating parameters of transmission systems beyond any Transmission Operator’s vision.
Reserve Sharing Group	RSG	A group whose members consist of two or more Balancing Authorities that collectively maintain, allocate, and supply operating reserves required for each Balancing Authority’s use in recovering from contingencies within the group. Scheduling energy from an Adjacent Balancing Authority to aid recovery need not constitute reserve sharing provided the transaction is ramped in over a period the supplying party could reasonably be expected to load generation in (e.g., ten minutes). If the transaction is ramped in quicker, (e.g., between zero and ten minutes), then, for the purposes of disturbance control performance, the areas become a Reserve Sharing Group.
Resource Planner	RP	The entity that develops a long-term (generally one year and beyond) plan for the resource adequacy of specific <b>Loads</b> (customer demand and energy requirements) within a Planning Authority area.
Transmission Owner	TO	The entity that owns and maintains transmission Facilities.



Function Type	Acronym	Definition/Discussion
Transmission Operator	TOP	The entity responsible for the reliability of its local transmission system and operates or directs the operations of the transmission Facilities.
Transmission Planner	TP	The entity that develops a long-term (generally one year and beyond) plan for the reliability (adequacy) of the interconnected bulk electric transmission systems within its portion of the Planning Authority area.
Transmission Service Provider	TSP	The entity that administers the transmission tariff and provides Transmission Service to Transmission Customers under applicable Transmission Service agreements.

III. Entities identified in Part II above as being subject to Registration as an LSE, DP, GO, GOP, TO, or TOP should be excluded from the Compliance Registry for these functions if they do not meet any of the criteria listed below:

III (a) Load-Serving Entity:

- III.a.1 Load-Serving Entity peak **Load** is > 25 MW and is directly connected to the Bulk Power (>100 kV) System, or;
- III.a.2 Load-Serving Entity is designated as the responsible entity for Facilities that are part of a required underfrequency **Load** shedding (UFLS) program designed, installed, and operated for the protection of the Bulk Power System, or;
- III.a.3 Load-Serving Entity is designated as the responsible entity for Facilities that are part of a required undervoltage **Load** shedding (UVLS) program designed, installed, and operated for the protection of the Bulk Power System.  
*[Exclusion: A Load-Serving Entity will not be registered based on these criteria if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, Balancing Authority, Transmission Operator, generation and transmission cooperative or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.]*
- III.a.4 Distribution Providers registered under the criteria in III.b.1 or III.b.2 will be registered as a Load Serving Entity (LSE) for all **Load** directly connected to their distribution facilities.

*[Exclusion: A Distribution Provider will not be registered based on this criterion if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, Balancing Authority, Transmission Operator, generation and transmission cooperative, or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.]*

III(b) Distribution Provider:

- III.b.1 Distribution Provider system serving >25 MW of peak **Load** that is directly connected to the Bulk Power System.

*[Exclusion: A Distribution Provider will not be registered based on this criterion if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, Balancing Authority, Transmission Operator, generation and transmission cooperative, or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.]* or;

- III.b.2 Distribution Provider is the responsible entity that owns, controls, or operates Facilities that are part of any of the following Protection Systems or programs designed, installed, and operated for the protection of the Bulk Power System:

- a required UFLS program.
- a required UVLS program.
- a required Special Protection System.
- a required transmission Protection System.

*[Exclusion: A Distribution Provider will not be registered based on these criteria if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, Balancing Authority, Transmission Operator, generation and transmission cooperative, or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.]*

III(c) Generator Owner/Operator:

- III.c.1 Individual generating unit > 20 MVA (gross nameplate rating) and is directly connected to the Bulk Power System, or;
- III.c.2 Generating plant/facility > 75 MVA (gross aggregate nameplate rating) or when the entity has responsibility for any facility consisting of one or

more units that are connected to the Bulk Power System at a common bus with total generation above 75 MVA gross nameplate rating, or;

III.c.3 Any generator, regardless of size, that is a Blackstart Resource material to and designated as part of a Transmission Operator entity's restoration plan, or;

III.c.4 Any generator, regardless of size, that is material to the reliability of the Bulk Power System.

*[Exclusions:*

*A Generator Owner/Operator will not be registered based on these criteria if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, generation and transmission cooperative or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.*

*As a general matter, a customer-owned or operated generator/generation that serves all or part of retail **Load** with electric energy on the customer's side of the retail meter may be excluded as a candidate for Registration based on these criteria if (i) the net capacity provided to the Bulk Power System does not exceed the criteria above or the Regional Entity otherwise determines the generator is not material to the Bulk Power System and (ii) standby, back-up and maintenance power services are provided to the generator or to the retail **Load** pursuant to a binding obligation with another Generator Owner/Operator or under terms approved by the local regulatory authority or the Federal Energy Regulatory Commission, as applicable.]*

III(d) Transmission Owner/Operator:

III.d.1 An entity that owns/operates an integrated transmission Element associated with the Bulk Power System 100 kV and above, or lower voltage as defined by the Regional Entity necessary to provide for the Reliable Operation of the interconnected transmission grid; or

III.d.2 An entity that owns/operates a transmission Element below 100 kV associated with a Facility that is included on a critical Facilities list that is defined by the Regional Entity.

*[Exclusion: A Transmission Owner/Operator will not be registered based on these criteria if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, such as a Load-Serving Entity, generation and transmission cooperative*

*or joint action agency as described in Sections 501 and 507 of the NERC Rules of Procedure.*

IV. Joint Registration Organization and applicable Member Registration.

Pursuant to FERC's directive in paragraph 107 of Order No. 693, NERC's rules pertaining to joint Registrations and Joint Registration Organizations are now found in Section 501 and 507 of the NERC Rules of Procedure.

V. If NERC or a Regional Entity encounters an organization that is not listed in the Compliance Registry, but which should be subject to the Reliability Standards, NERC or the Regional Entity is obligated and will initiate actions to add that organization to the Compliance Registry, subject to that organization's right to challenge as provided in Section 500 of NERC's Rules of Procedure and as described in Note 3 below.

**Notes to the above Criteria**

1. The above are general criteria only. The Regional Entity considering Registration of an organization not meeting (e.g., smaller in size than) the criteria may propose Registration of that organization if the Regional Entity believes and can reasonably demonstrate<sup>4</sup> that the organization is a Bulk Power System owner, or operates, or uses Bulk Power System assets, and is material to the reliability of the Bulk Power System. Similarly, the Regional Entity may exclude an organization that meets the criteria described above as a candidate for Registration if it believes and can reasonably demonstrate to NERC that the Bulk Power System owner, operator, or user does not have a material impact on the reliability of the Bulk Power System.
2. An organization not identified using the criteria, but wishing to be registered, may request that it be registered. For further information refer to: NERC Rules of Procedure, Section 500 – Organization Registration and Certification; Part 1.3.
3. An organization may challenge its Registration within the Compliance Registry. NERC or the Regional Entity will provide the organization with all information necessary to timely challenge that determination including notice of the deadline for contesting the determination and the relevant procedures to be followed as described in the NERC Rules of Procedure; Section 500 – Organization Registration and Certification.
4. If an entity is part of a class of entities excluded based on the criteria above as individually being unlikely to have a material impact on the reliability of the Bulk Power System, but that in aggregate have been demonstrated to have such an impact it may be registered for applicable Reliability Standards and Requirements irrespective of other considerations.

---

<sup>4</sup> The reasonableness of any such demonstration will be subject to review and remand by NERC itself, or by any Applicable Governmental Authority.